

XCFR2.E202113 - Terminal Blocks - Component

Terminal Blocks - Component

ANYTEK TECHNOLOGY CORP

5F-6 No 77 Sec 1 Xintai 5th Rd
Xizhi District
New Taipei City, 22101 Taiwan

E202113

Cat. No.	Wire Range	Wire Type	FW	TQ Lb In.	V	A	UG	CA
TA(@1a)	14-26 Str	Cu	1	2.6	250	16	D	2(105), Note 2
TA(@1a)	14-26 Sol	Cu	2	2.6	250	16	D	2(105), 4, Note 2
TAA(@1a)	14-26 Str	Cu	1	2.6	250	16	D	2(65)
TAA(@1a)	14-26 Sol	Cu	2	2.6	250	16	D	2(65), 4
TB(@1a)	14 Sol	Cu	2	2.6	250	16	D	2(105), 4, Note 2
TBA(@1a)	14 Sol	Cu	2	2.6	250	16	D	2(65), 4
TC(@1)	16 Str	Cu	1	2.6	250	16	D	2(105)
TC(@1)	14 Sol	Cu	2	2.6	250	16	D	2(105), 4
TCA(@1)	16 Str	Cu	1	2.6	250	16	D	2(65)
TCA(@1)	14 Sol	Cu	2	2.6	250	16	D	2(65), 4
TD(@1a)	16 Str	Cu	1	2.6	250	16	D	2(105), Note 2

TD(@1a)	14 Sol	Cu	2	2.6	250	16	D	2(105), 4, Note 2
TDA(@1a)	16 Str	Cu	1	2.6	250	16	D	2(65)
TDA(@1a)	14 Sol	Cu	2	2.6	250	16	D	2(65), 4
TE(@1a)	16-26 Str	Cu	1	1.7	125	10	B, D	2(105)
TEA(@1a)	16-26 Str	Cu	1	1.7	125	10	B, D	2(65)
TEA(@1a)	16-26 Sol	Cu	2	1.7	125	10	B, D	2(65), 4
TEA(@1a)	16-26 Sol	Cu	2	1.7	125	10	B, D	2(65), 4
TF(@1a)	16-26 Str	Cu	1	1.7	125	10	B, D	2(105), Note 2
TF(@1a)	16-26 Sol	Cu	2	1.7	125	10	B, D	2(105), 4, Note 2
TFA(@1a)	16-26 Str	Cu	1	1.7	125	10	B, D	2(65)
TFA(@1a)	16-26 Sol	Cu	2	1.7	125	10	B, D	2(65), 4
TM(+)	14-22 Str	Cu	2	3.5	400	10	D	2(105), 4
TM(@@169)	14-22 Str	Cu	2	3.5	400	10	D	2(105), 4
TG(@2)	12-22 Sol	Cu	2	3.5	300	10	B, D	2(105), 4
TG(@2)	12-22 Str	Cu	1	3.5	300	10	B, D	2(105)
TI(@@425) or TI(@@426) or TI(@@427) or TI(@@428)	12-22, Str/Sol	Cu	2	3.5	300	16	B, D	2(115), 4
TI(@3) or TI(@4)	12-22 Str	Cu	1	3.5	300	10	B, D	2(115)

TI(@3) or TI(@4)	12-22 Sol	Cu	2	3.5	300	10	B, D	2(115), 4
TK(@5), TL(@5), TK(@@364), TL(@@364), TK(@@365), TL(@@365)	12-22 Str	Cu	1	3.5	300	10	B, D	2(115)
TK(@5), TL(@5), TK(@@364), TL(@@364), TK(@@365), TL(@@365)	12-22 Sol	Cu	2	3.5	300	10	B, D	2(115), 4
TO(@6)	16-26 Str	Cu	1	3.5	300	10	B, D	2(105)
TO(@6)	16-26 Sol	Cu	2	3.5	300	10	B, D	2(105), 4
T2(@7)	12-30	Cu	2	3.5	300	15	B, D	2(105), 4
T2(@@170)	12-30	Cu	2	3.5	300	15	B, D	2(105), 4
T2(@@170A)	12-30	Cu	2	3.5	300	15	B, D	2(105), 4
T2(@@171)	12-30	Cu	2	3.5	300	15	B, D	2(105), 4
T2(@@172)	12-30	Cu	2	3.5	300	15	B, D	2(105), 4
T2(@@172A)	12-30	Cu	2	3.5-5.3	300	15	B, D	2(105), 4
T2(@@172B)	12-30	Cu	2	3.5-5.3	300	15	B, D	2(105), 4
T2(@@172C)	12-30	Cu	2	3.5-5.3	300	15	B, D	2(105), 4
T2(@@172D)	12-30	Cu	2	3.5-5.3	300	15	B, D	2(105), 4
T3(@@359), T3(@@360), T3(@@361), T3(@@362), T3(@@363)	14-26 Str/Sol	Cu	1	3.5	300	8	B, D	2(115)

T4(@7)	12-18 Str	Cu	1	3.5	300	10	B, D	2(105)
T4(@7)	12-18 Sol	Cu	2	3.5	300	10	B, D	2(105), 4
T6(@7)	16-26 Str	Cu	1	1.7	125	10	B, D	2(105)
T6(@7)	16-26 Sol	Cu	2	1.7	125	10	B, D	2(105), 4
T5(@@359)	16-26 Str/Sol	Cu	2	1.7	125	10	B	2 (115), 4, Note 6
T5(@@304)	16-26 Str/Sol	Cu	2	1.7	125	10	B	2 (115), 4, Note 6
T5(@@305)	16-26 Str/Sol	Cu	2	1.7	125	10	B	2 (115), 4
T5(@@305a)	16-26 Str/Sol	Cu	2	1.7	125	10	B	2 (130), 4
TN(@8)	18 Str	Cu	1	—	300	2	D	2(105)
TN(@8)	18 Sol	Cu	2	—	300	2	D	2(105), 4
TA(@9)	14-22 Str	Cu	1	3.5	250	16	B	2(105), Note 1
TA(@9a)	14-22 Str	Cu	1	3.5	250	16	B	2(105), Note 1
T7(@10)	10-24 Str	Cu	1	3.5	300	25	B	2(105)
YC(@11)	16-26 Str	Cu	1	3.5	300	10	B	2(105)
YC(@11)	16-26 Sol	Cu	2	3.5	300	10	B	2(105), 4
YD(@12)	12-24 Str	Cu	1	3.5	300	10	B, D	2(115)
YD(@@320)	12-24 Str	Cu	1	3.5	300	10	B, D	2(115), Note 2
YE(@12), (@@323)	12-24 Str	Cu	1	3.5	300	10	B, D	2(115)

YE(@@322)	12-24 Str	Cu	1	3.5	300	10	B, D	2(115), Note 2
YF(@12)	12-24 Str	Cu	1	3.5	300	10	B, D	2(105)
YF(@@321)	12-24 Str	Cu	1	3.5	300	10	B, D	2(105), Note 2
YD(@12),	12-24 Sol	Cu	2	3.5	300	10	B, D	2(115), 4
YD(@@320)	12-24 Sol	Cu	2	3.5	300	10	B, D	2(115), 4, Note 2
YE(@12), (@@323)	12-24 Sol	Cu	2	3.5	300	10	B, D	2(115), 4
YE(@@322)	12-24 Sol	Cu	2	3.5	300	10	B, D	2(115), 4, Note 2
YF(@12)	12-24 Sol	Cu	2	3.5	300	10	B, D	2(105), 4
YF(@@321)	12-24 Sol	Cu	2	3.5	300	10	B, D	2(105), 4, Note 2
YK311(##1)	16-22 Str	Cu	1	5.3	250	15	B	2(115)
	16-22 Sol		2					2(115), 4
YK312(##1)	16-22 Str	Cu	1	5.3	250	15	B	2(115)
	16-22 Sol		2					2(115), 4
YK313(##1)	16-22 Str	Cu	1	5.3	250	15	B	2(115)
	16-22 Sol		2					2(115), 4
YK313(@@405)	16-22 Str	Cu	1	5.3	250	15	B	2(130)
	16-22 Sol		2					2(130), 4
YK314(##1)	16-22 Str	Cu	1	5.3	250	15	B	2(115)
	16-22 Sol		2					2(115), 4

YK315(##1), YK316(##1)	16-22 Str	Cu	1	5.3	250	15	B	2(115)
	16-22 Sol		2					2(115), 4
YK315(##1a)	16-22 Str	Cu	1	5.3	250	15	B	2(125)
	16-22 Sol		2					2(125), 4
YK441(##1)	14-22 Sol	Cu	1	10.54	300	25	B	2(115)
YK442(##1)	14-22 Sol	Cu	1	10.54	300	25	B	2(115)
YK443(##1)	14-22 Sol	Cu	1	10.54	300	25	B	2(115)
YK444(##1)	14-22 Sol	Cu	1	10.54	300	25	B	2(115)
YK445(##1)	14-22 Sol	Cu	1	10.54	300	25	B	2(115)
YK446(##1)	14-22 Sol	Cu	1	10.54	300	25	B	2(115)
YK447(##1)	14-22 Sol	Cu	1	10.54	300	25	B	2(115)
YK511(##2)	14-22 Sol	Cu	1	8.8	300	25	B	2(115)
YK512(##2)	14-22 Sol	Cu	1	8.8	300	25	B	2(115)
YK513(##2)	14-22 Sol	Cu	1	8.8	300	25	B	2(115)
YK514(##2)	14-22 Sol	Cu	1	8.8	300	25	B	2(115)
YK515(##2), YK-516(##2)	14-22 Sol	Cu	1	8.8	300	25	B	2(115)
YK551(##3)	12-22 Str	Cu	1	15.8	300	30	B	2(115)
YK552(##3)	12-22 Str	Cu	1	15.8	300	30	B	2(115)
YK553(##3)	12-22 Str	Cu	1	15.8	300	30	B	2(115)
YK554(##3), YK555(##3)	12-22 Str	Cu	1	15.8	300	30	B	2(115)
YK611(##3)	12-22 Str	Cu	1	8.8	300	25	B	2(115)
	12-22 Sol		2					2(115), 4
YK612(##3)	12-22 Str	Cu	1	8.8	300	25	B	2(115)

	12-22 Sol		2					2(115), 4
YK613(##3)	12-22 Str	Cu	1	8.8	300	25	B	2(115)
	12-22 Sol		2					2(115), 4
YK614(##3)	12-22 Str	Cu	1	8.8	300	25	B	2(115)
	12-22 Sol		2					2(115), 4
YK615(##3), YK616(##3)	12-22 Str	Cu	1	8.8	300	25	B	2(115)
	12-22 Sol		2					2(115), 4
YK221(##2)	18-22 Str/Sol	Cu	2	5.3	250	10	B, D	2(115), 4
YK222(##2)	18-22 Str/Sol	Cu	2	5.3	250	10	B, D	2(115), 4
YK223(##2)	18-22 Str/Sol	Cu	2	5.3	250	10	B, D	2(115), 4
YK224(##2)	18-22 Str/Sol	Cu	2	5.3	250	10	B, D	2(115), 4
YK331(##3)	12-22 Str/Sol	Cu	2	8.8	300	20	B	2(115), 4
YK332(##3)	12-22 Str/Sol	Cu	2	8.8	300	20	B	2(115), 4
YK333(##3)	12-22 Str/Sol	Cu	2	8.8	300	20	B	2(115), 4
YK334(##3)	12-22 Str/Sol	Cu	2	8.8	300	20	B	2(115), 4
YK335(##3)	12-22 Str/Sol	Cu	2	8.8	300	20	B	2(115), 4
YK411(##3)	12-22 Str/Sol	Cu	2	8.8	300	20	B	2(115), 4
YK412(##3)	12-22 Str/Sol	Cu	2	8.8	300	20	B	2(115), 4
YK413(##3)	12-22 Str/Sol	Cu	2	8.8	300	20	B	2(115), 4
YK414(##3)	12-22 Str/Sol	Cu	2	8.8	300	20	B	2(115), 4
YK415(##3)	12-22 Str/Sol	Cu	2	8.8	300	20	B	2(115), 4

YK421(##3)	12-22 Str/Sol	Cu	2	8.8	300	20	B	2(115), 4
TP (@@1)	12-24 Str/Sol	Cu	2	3.5	300	10	B or D	2(120), 4
TU (@@2)	12-22 Str/Sol	Cu	2	3.5	300	20	B	2(120), 4
						Note A	D	
HA (@@3)	14-24 Sol/Str	Cu	2	—	300	10	B, D	2(120),4
ED (@@4) (#1)	16-24 Str/Sol	Cu	2	2.17	300	8	B	2(120),4
ED (@@4) (#2)	16-24 Str/Sol	Cu	2	2.17	300	8	B	2(120),4
VJ (@@5)	12-30 Sol/Str	Cu	2	3.5	300	20	B, D	2(120),4, Note 2
VJ (@@283)								
VJ (@@284)								
VJ (@@285)								
VJ (@@285A)								
VD (@@6)	16 - 28 Sol/Str	Cu	2	1.7	300	8	B, D	2(115),4, #7
VE (@@7) VE (@@7A) VE (@@7B) VE (@@7C)	—	Cu	1	—	300	8	B, D	2(115), #7
HC(@@8)	16-20 Sol/Str	Cu	1	—	300	5	B, D	2(120)
TJ (@@9),	16-28 Sol/Str	Cu	2	3	300	10	B, D	2(115), 4, #8
TJ (@@120)								

TJ (@@286),	16-26 Sol/Str							
TJ (@@287)								
TJ (@@218)	16-28 Sol/Str	Cu	2	2	300	10	B, D	2(115), 4, #8
TJ (@@288)	16-26 Sol/Str							
TJ (@@219)	16-28 Sol/Str	Cu	2	2	300	10	B, D	2(115), 4, #8
TJ (@@289)	16-26 Sol/Str							
OQ (@@10)	—	—	1	—	300	10	B, D	2(115), #8, #13, #76
OQ (@@121)								
OQ (@@10A)	—	—	1	—	300	10	B, D	2(120), #8, #13
OQ (@@10B)	—	—	1	—	300	10	B, D	2(130), #8, #13
OQ (@@10C)	—	—	1	—	300	10	B, D	2(130), #8
OQ (@@10D)	—	—	1	—	300	10	B, D	2(130), #8
TJ (@@11) TJ (@@263)	12-24 Sol/Str	Cu	2	5	300	20	B	2(115), 4, #8
						Note A	D	
TJ (@@122) TJ (@@267)								
OQ (@@12) OQ (@@269) OQ (@@474) OQ (@@475) OQ (@@12C)	—	—	1	—	300	20	B	2(115), #8, #13, #56a

						Note A	D	
OQ (@@12D) OQ (@@265B)	—	—	1	—	300	20	B	2(130), #8, #43
						Note A	D	
OQ (@@123) OQ (@@270)								
OQ (@@12A)	—	—	1	—	300	20	B	2(130), #8, #13
						Note A	D	
OQ (@@12B)	—	—	1	—	300	20	B	2(130), #8, #13
						Note A	D	
TJ (@@173) TJ (@@265)	12-24 Sol/Str	Cu	2	5	300	20	B	2(115), 4, #8
						Note A	D	
TJ (@@174) TJ (@@265A)	12-24 Sol/Str	Cu	2	5	300	20	B	2(115), 4, #8
						Note A	D	
TJ (@@220) TJ (@@264)	12-24 Sol/Str	Cu	2	3.9	300	20	B	2(115), 4, #8
						Note A	D	
TJ (@@221) TJ (@@266)	12-24 Sol/Str	Cu	2	3.9	300	20	B	2(115), 4, #8

						Note A	D	
TJ (@@222) TJ (@@268)	12-24 Sol/Str	Cu	2	3.9	300	20	B	2(115), 4, #8
						Note A	D	
TJ (@@223)	12-24 Sol/Str	Cu	2	3.9	300	20	B	2(115), 4, #8
						Note A	D	
OQ (@@175), OQ (@@175A), OQ (@@175B)	—	—	1	—	300	20	B	2(115), #8, #13
						Note A	D	
OQ (@@175C)	—	—	1	—	300	20	B	2(130), #8
						Note A	D	
TJ (@@247), TJ (@@247a)	12 - 24, Str/Sol	Cu	2	5	300	12	B	2 (115), 4, #8
					300	Note A	D	
OQ (@@248)	—	—	1	—	300	12	B	2 (115), #8
					300	Note A	D	
OQ (@@249)	—	—	1	—	300	12	B	2 (115), #8
					300	Note A	D	
TJ (@@250) TJ (@@250a)	12 - 24, Str/Sol	Cu	2	5	300	12	B	2 (115), 4, #8
					300	Note A	D	

OQ (@@251)	—	—	1	—	300	12	B	2 (115), #8
					300	Note A	D	
YL (@@13), YL (@@366), YL (@@368)	12-22 Sol/Str	Cu	2	3.5	300	20	B	2(115), 4, Note 7
YL (@@14), YL (@@367), YL (@@369)	14-22 Sol/Str	Cu	2	3.5	300	15	B	2(115), 4, Note 7
HE(@@15)	22-28 Sol/Str	Cu	2	—	150	4	B	2(115), 4
HE(@@15a)	22-28 Sol/Str	Cu	2	—	150	4	B, D	2(115), 4
TR (@@16)	12 - 22 Str/Sol	Cu	2	2.4	300	20	B	2(115), 4
T7 (@@17)	12 - 24 Str/Sol	Cu	2	4.3	300	25	B	2(115), 4
T7 (@@18)								
TS (@@19)	16-28 Str/Sol	Cu	2	1.7	300	8	B	2(115), 4, #9, #76
TS (@@124)	16-28 Str/Sol	Cu	2	1.7	300	8	B	2(115), 4, #9, #76
VK (@@20)	—	—	1	—	300	8	B	2(115), #9
VK (@@20A)	—	—	1	—	300	8	B	2(130), #9
VK (@@125)	—	—	1	—	300	8	B	2(115), #9
TS (@@21)	12-24 Str/Sol	Cu	2	3.5	300	15	B	2(115), 4, #10
TS (@@126)	12-24 Str/Sol	Cu	2	3.5	300	15	B	2(115), 4, #10
VK (@@22)	—	—	1	—	300	15	B	2(115), #10
VK (@@22A)	—	—	1	—	300	15	B	2(130), #10
VK (@@127)	—	—	1	—	300	15	B	2(115), #10

VK (@@127A)	—	—	1	—	300	15	B	2(115), #10
EI (@@23)	2-20 Str/Sol	Cu	2	30.4	600	120	B, C	2(115), 4
EI(@@23-1)	2-20 Str/Sol	Cu	2	36.5	600	125	B, C	2(115), 4
VP (@@24)	8-22 Str/Sol	Cu	2	14	300	50	B	2(115), 4
VP (@@24-1)	8-22 Str/Sol	Cu	2	19	300	57	B	2(115), 4
V4 (@@25)	6-22 Str/Sol	Cu	2	8.7	600	65	B, C	2(115), 4
VV(@@26)	10-30 Str/Sol	Cu	2	5.2	300	30	B	2(115), 4, Note 3
HH(@@27)	14-28, Str/Sol	Cu	2	—	300	15	B	2(115), 4
					150		B, D	
HD(@@28)	16-22, Str/Sol	Cu	2	—	250	12	B	2(115), 4
					150		B, D	
VI(@@29), (@@324)	12-28, Str/Sol	Cu	2	3.5	300	16	B, D	2(115), 4
VI(@@165), (@@325)	12-28, Str/Sol	Cu	2	3.5	300	16	B, D	2(115), 4
YO(@@30), YO(@@30a)	16-24 Str/Sol	Cu	2	1.7	300	10	B	2(115), 4
VH(@@31)	12-24 Str/Sol	Cu	2	4.3	300	20	B	2(115), 4, #11
					Note A	Note A	D	
VL(@@32)	—	Cu	1	—	300	20	B	2(115), #11
						Note A	D	

VM(@@33)	16-28 Str/Sol	Cu	2	1.7	300	10	B	2(115), 4, #11
VL(@@34)	—	Cu	1	—	300	10	B	2(115), #11
VM(@@35)	16-28 Str/Sol	Cu	2	1.7	300	10	B, D	2(115), 4, #11
VZ(@@36)	—	Cu	1	—	300	10	B, D	2(115), #11
VM(@@37)	12-22 Str/Sol	Cu	2	3.5	300	20	B	2(115), 4, #11
						Note A	D	
VL(@@38)	—	Cu	1	—	300	20	B	2(115), #11
						Note A	D	
TJ(@@39)	16-26 Str/Sol	Cu	2	1.7	300	10	B	2(115), 4, #11
VL(@@40)	—	Cu	1	—	300	10	B	2(115), #11
HB(@@41), HB(@@370), HB(@@374)	16-20, Str/Sol	Cu	2	—	300	10	B, D	2(115), 4
HB(@@42), HB(@@371), HB(@@372), HB(@@373)	14-20, Str/Sol	Cu	2	—	300	10	B, D	2(115), 4
TC(@@43) TC(@@43A)	14-22, Str/Sol	Cu	2	2.6	300	16	B	2(115), 4
					300	Note A	D	
TC(@@44) TC(@@271)	14-22, Str/Sol	Cu	2	2.6	300	16	B	2(115), 4, Note 2
					300	Note A	D	
TC(@@246)	14-22, Str/Sol	Cu	2	2.6	300	16	B	2(130), 4, Note 2

					300	Note A	D	
TH(@@197)	14-22, Str/Sol	Cu	2	3.5	300	15	B	2(115), 4, #12, Note 2
						Note A	D	
TH(@@458a) TH(@@458b)	14-22, Str/Sol	Cu	2	3.5	300	8	B, D	2(115), 4, #12
TT(@@45)	16-22, Str/Sol	Cu	2	1.7	300	10	B, D	2(115), 4, #12, Note 2
TH(@@198)	14-22, Str/Sol	Cu	2	3.5	300	15	B	2(115), 4, #12
						Note A	D	
TT(@@46)	16-22, Str/Sol	Cu	2	1.7	300	10	B, D	2(115), 4, #12
OP(@@47)	—	Cu	1	—	300	15	B	2(115), #12
						Note A	D	
OP(@@459a) OP(@@459b)	—	Cu	1	—	300	8	B, D	2(115), #12
TH(@@48)	16-28, Str/Sol	Cu	2	1.7	300	10	B	2(115), 4, #12, Note 2
TH(@@49)	16-28, Str/Sol	Cu	2	1.7	300	10	B	2(115), 4, #12
TH(@@50),	16-28, Str/Sol	Cu	2	1.7	300	10	B	2(115), 4, #12, Note 2
TH(@@128)								
TT(@@51)	16-28, Str/Sol	Cu	2	1.7	300	10	B	2(115), 4, #12, Note 2

OP(@@52)	—	Cu	1	—	300	10	B	2(115), #12
YK40(@@53), YK40(@@53a)	12-22, Str/Sol	Cu	2	7	300	20	B	2(115), 4
						Note A	D	
YK50(@@54)	12-22, Str/Sol	Cu	2	12	300	20	B	2(115), 4
						Note A	D	
YK60(@@54)	12-22, Str/Sol	Cu	2	12	300	20	B	2(115), 4
						Note A	D	
HI(@@55), HI(@@378), HI(@@379), HI(@@380)	12-28, Str/Sol	Cu	2	—	300	15	B	2(115), 4, #13
						Note A	D	
HW(@@56)	20-28, Str/Sol	Cu	2	—	125	4	B, D	2(115), 4, #13
HW(@@57), (@@291), (@@291a), (@@293)	12-26, Str/Sol	Cu	2	—	300	10	B, D	2(115), 4, #13
HN(@@57)	12-26, Sol	Cu	2	—	300	10	B, D	2(115), 4, #13
	14-26, Str							
OQ(@@57a), OQ(@@294)	—	Cu	1	—	300	15	B, D	2(115), #13
OQ(@@57b)	—	Cu	1	—	125	4	B, D	2(115), #13
OQ(@@57c)	—	Cu	1	—	300	10	B, D	2(115), #13
HM (@@58), HM (@@375), HM (@@376), HM (@@377)	12-28, Str/Sol	Cu	2	—	250	8	B, D	2(115), 4

ADR-1.5000000G	14-30, Str/Sol	Cu	2	2	300	15	B, C	2(115), 4
					Note A	Note A	D	
ADR-2.5B00000G	12-30, Str/Sol	Cu	2	6	600	20	B, C	2(115), 4
					Note A	Note A	D	
ADR-300000000G	12-24, Str/Sol	Cu	2	5	600	20	B, C	2(115), 4
					Note A	Note A	D	
ADR-500000000G	10-30, Str/Sol	Cu	2	6	600	30	B, C	2(115), 4
					Note A	Note A	D	
ADR-600000000G	8-24, Str/Sol	Cu	2	13	600	48	B, C	2(115), 4
					Note A	Note A	D	
ADR-100000000G	6-24, Str/Sol	Cu	2	14	600	65	B, C	2(115), 4
					Note A	Note A	D	
EM(@@59)	12-22 Str/Sol	Cu	2	4	300	20	B	2(115), 4, #14
OQ(@@60)	—	—	1	—	300	20	B	2(115), #14
EM(@@326)	12-22 Str/Sol	Cu	2	4	300	12	B	2(115), 4, #14
OQ(@@327)	—	—	1	—	300	12	B	2(115), #14

EM(@@61)	12-22 Str/Sol	Cu	2	4	300	20	B	2(115), 4, #15
OQ(@@62)	—	—	1	—	300	20	B	2(115), #15
OQ(@@176)	—	—	1	—	300	20	B	2(115), #15
EM(@@328)	12-22 Str/Sol	Cu	2	4	300	12	B	2(115), 4, #15
OQ(@@329)	—	—	1	—	300	12	B	2(115), #15
OQ(@@330)	—	—	1	—	300	12	B	2(115), #15
TV(@@63)	16-28 Str/Sol	Cu	2	1.7	300	10	B, D	2(115), 4
HC (@@64)	16-22, Str/Sol	Cu	2	—	300	6	B	2(115), 4
HC (@@64a), HC (@@64b)	16-22, Str/Sol	u	2	—	300	6	B, D	2(115), 4
HC (@@65a)	20-26, Str/Sol	Cu	2	—	300	2	B, D	2(115), 4
HC (@@65b)	20-26, Str/Sol	Cu	2	—	150	2	B	2(115), 4
HC (@@145a)	20-26, Str/Sol	Cu	2	—	300	2	B, D	2(115), 4
HC (@@145b)	Str/Sol	Cu	2	—	150	2	B	2(115), 4
HY (@@66)	18-22Sol	Cu	2	—	300	7	B, D	2(115), 4, Note 2
HF (@@67)	16-20,Sol	Cu	2	—	300	10	B, D	2(115), 4
HV (@@68)	16-20,Str/Sol	Cu	2	—	300	8	B, D	2(115), 4
HF (@@492)	16-20,Str/Sol	Cu	2	—	300	10	B, D	2(115), 4
ADR-10JD00000G	6-24,Str/Sol	Cu	2	13	—	—	B, C	2(115), 4, #16

ADR-16JD00000G	4-12,Str	Cu	2	12	—	—	B, C	2(115), 4, #16
ADR-35JD00000G	2-14,Str	Cu	2	30	—	—	B, C	2(115), 4, #16
ADR-3JD000000G	12-28,Str/Sol	Cu	2	4	—	—	B, C	2(115), 4, #16
ADR-5JD000000G	10-26,Str/Sol	Cu	2	4	—	—	B, C	2(115), 4, #16
ADR-6JD000000G	8-24,Str/Sol	Cu	2	12	—	—	B, C	2(115), 4, #16
T4 (@@69)	12-20, SOL/STR	Cu	2	3.5	300	10	B, D	2(115), 4
T4 (@@70)	12-20, SOL/STR	Cu	2	3.5	300	10	B, D	2(115), 4
VY (@@71)	14-22, SOL/STR	Cu	2	3.5	300	15	B	2(115), 4, Note 2
					Note A	Note A	D	
VY (@@187)	14-22, SOL/STR	Cu	2	3.5	300	15	B	2(120), 4, Note 2
					300	Note A	D	
VY (@@260)	14-22, SOL/STR	Cu	2	3.5	300	15	B	2(115), 4, Note 2
					Note A	Note A	D	
VB(@@72), VB(@@381)	10-30 SOL/STR	Cu	2	4.5	300	20	B	2(115), 4, #17
					Note A	Note A	D	
VC(@@73), VC(@@382)	—	—	1	—	300	20	B	2(115), #17

					Note A	Note A	D	
ADR160000000G	4-20, SOL/STR	Cu	2	11	800	80	E	2(115), 4
ADR350000000G	1-14, STR	Cu	2	38	800	120	E	2(115), 4
ADR500000000G	3/0-8, STR	Cu	2	39	1000	180	E	2(115), 4
ADR950000000G	300 kcmil - 4 AWG, STR	Cu	2	70	1000	280	E	2(115), 4
ADR150000000G	350 kcmil - 2 AWG, STR	Cu	2	94	1000	285	E	2(115), 4
TG (@@74) TG (@@272)	12-24 Str/Sol	Cu	2	3.5	300	15	B	2(115), 4, Note 2
					Note A	Note A	D	
YK77 (@@75)	14-20 Str/Sol	Cu	2	12	300	10	B, D	2(115), 4, #18
HA (@@76)	20-26 Str/Sol	Cu	2	—	150	2	B	2(115), 4
TJ (@@77)	16-26 SOL/STR	Cu	2	2.5	300	10	B	2(75), 4, #19
OQ(@@78)	—	—	1	—	300	10	B	2(75), #19
TJ (@@79)	12-24 SOL/STR	Cu	2	3.5	300	20	B	2(75), 4, #20
					Note A	Note A	D	
OQ(@@80)	—	—	1	—	300	20	B	2(75), #20
					Note A	Note A	D	
TJ (@@81)	12-24 SOL/STR	Cu	2	3.5	300	20	B	2(75), 4, #21

					Note A	Note A	D	
OQ(@@82)	—	—	1	—	300	20	B	2(75), #21
					Note A	Note A	D	
TJ (@@83)	12-24 SOL/STR	Cu	2	3.5	300	20	B	2(75), 4, #21
					Note A	Note A	D	
OQ(@@84)	—	—	1	—	300	20	B	2(75), #21
					Note A	Note A	D	
YO (@@85)	16-24 SOL/STR	Cu	2	1.7	300	10	B	2(115), 4
YO (@@86)								
YP (@@85)	16-24 SOL/STR	Cu	2	1.7	300	10	B	2(115), 4
YP (@@86)								
YQ (@@87)	16-24 SOL/STR	Cu	2	1.7	300	10	B	2(115), 4
YQ (@@88)								
VN (@@89)	18-30 Str/Sol	Cu	2	1.3	150	6	B	2(115),4
EO (@@90)	12-28 Str/Sol	Cu	2	4.5	300	15	B	2(115), 4, #22
					Note A	Note A	D	
EP (@@91)	—	—	1	—	300	15	B	2(115), #22
					Note A	Note A	D	

EO (@@92)	12-28 Str/Sol	Cu	2	4.5	300	15	B	2(115), 4, #23
					Note A	Note A	D	
EP (@@93)	—	—	1	—	300	15	B	2(115), #23
					Note A	Note A	D	
EH (@@94)	16-28 Str/Sol	Cu	2	1.1	150	10	B, D	2(115), 4, #24, Note 2
OP (@@95)	—	—	1	—	150	10	B, D	2(120), #24
TO (@@96)	16-26 Str/Sol	Cu	2	3.5	300	10	B	2(115), 4, Note 2
HP (@@97)	18-22, Str/Sol, Style 1015	Cu	2	—	300	7	B, D	2(115), 4, #25
VZ (@@98)	—	—	1	—	300	7	B, D	2(115), #25
YC (@@99)	16 - 26 Str/Sol	Cu	2	3.5	300	10	B	2(115), 4, Note 2
YC (@@331)	16 - 26 Str/Sol	Cu	2	3.5	300	10	B	2(115), 4
YS (@@100)	16 - 26 Str/Sol	Cu	2	3.5	300	10	B	2(115), 4, Note 3
TS (@@101)	12 - 24 Str/Sol	Cu	2	3.5	300	15	B	2(115), 4, #26
					300	Note A	D	
					150	15	C	
TS (@@261)	12 - 24 Str/Sol	Cu	2	3.5	300	15	B	2(115), 4, #26
					300	Note A	D	

					150	15	C	
OQ(@@102)	—	—	1	—	300	15	B	2(115), #26
					300	Note A	D	
					150	15	C	
TS (@@252)	12 - 24, Str/Sol	Cu	2	3.5	300	15	B	2(115), 4, #26
					300	Note A	D	
TS (@@262)	12 - 24, Str/Sol	Cu	2	3.5	300	15	B	2(115), 4, #26
					300	Note A	D	
OQ (@@253)	—	—	1	—	300	15	B	2(115), #26
					300	Note A	D	
OQ (@@254)	—	—	1	—	300	15	B	2(115), #26
					300	Note A	D	
TS (@@255)	12 - 24, Str/Sol	Cu	2	3.5	300	12	B	2(115), 4, #26
					300	Note A	D	
					150	12	C	
OQ (@@256)	—	—	1	—	300	12	B	2(115), #26
					300	Note A	D	
					150	12	C	

TS (@@257)	12 - 24, Str/Sol	Cu	2	3.5	300	12	B	2(115), 4, #26
					300	Note A	D	
OQ (@@258)	—	—	1	—	300	12	B	2(115), #26
					300	Note A	D	
OQ (@@259)	—	—	1	—	300	12	B	2(115), #26
					300	Note A	D	
TX (@@103)	12 - 26 Str/Sol	Cu	2	3.5	300	10	B	2(115), 4, #27
EX (@@104)	—	—	1	—	300	10	B	2(115), #27
HZ (@@105)	16-20, SOL for Push-In Type Connections	Cu	2	—	300	2	B, D	2(115),4
HZ (@@105)	Style 1015, 20 AWG, SOL for Insulation Displacement Connections							
ER (@@106)	16/24 Str/Sol	Cu	2	1.7	300	10	B	2(115), 4, Note 2
T7 (@@107)	10 - 24 Str/Sol	Cu	2	8.9	300	30	B	2(115),4, Note 2
					300	Note A	D	
					150	30	C	
T7 (@@108)	10 - 24 Str/Sol	Cu	2	8.9	300	30	B	2(115), 4, Note 2

					300	Note A	D	
					150	30	C	
T7 (@@108a), T7 (@@108b), T7 (@@108c)	10 - 24 Str/Sol	Cu	2	8.9	300	30	B	2(115), 4
					300	Note A	D	
					150	30	C	
T7 (@@108d)	10 - 24 Str/Sol	Cu	2	8.9	300	30	B	2(115), 4
					300	Note A	D	
T7 (@@108e)	10 - 12 Str/Sol	Cu	2	9.5	300	32	B, D	2(115), 4
					150	32	C	
EY (@@109)	12 - 24 Str/Sol	Cu	2	4	300	20	B	2(115),4,#28
					300	Note A	D	
OQ (@@110)	—	—	1	—	300	20	B	2(115),#28
					300	Note A	D	
TA (@@111)	14 - 22 Str/Sol	Cu	2	3.5	300	15	B	2(115), 4, Note 2
					300	Note A	D	
TB (@@112)	14 - 22 Str/Sol	Cu	2	3.5	250	15	B	2(115), 4, Note 2
					250	Note A	D	
TQ (@@113)	14 - 22 Str/Sol	Cu	2	3.5	300	15	B	2(115), 4

					300	Note A	D	
TG (@@114)	12 - 22 Str/Sol	Cu	2	3.5	300	10	B, D	2(115), 4
TI (@@115)	12 - 22 Str/Sol	Cu	2	3.5	300	10	B, D	2(115), 4
TI (@@116)	12 - 22 Str/Sol	Cu	2	3.5	300	10	B, D	2(115), 4
T4 (@@117)	12 - 20 Str/Sol	Cu	2	3.5	300	10	B, D	2(115), 4
YM (@@118)	12 - 24 Str/Sol	Cu	2	3.5	300	10	B	2(115), 4, Note 3
YN (@@119)	12 - 24 Str/Sol	Cu	2	3.5	300	10	B	2(115), 4, Note 4
H2 (@@129)	10-24 Str/Sol	Cu	2	—	300	10	B, D	2(115), 4
H3 (@@130)	12-28 Str/Sol	Cu	2	—	300	10	B, D	2(115), 4
H3 (@@131)	12-28 Str/Sol	Cu	2	—	300	10	B, D	2(115), 4
ET (@@132), (@@332)	24-8 Str/Sol	Cu	2	7	300	32	B	2(115),4,#29
					300	Note A	D	
VC (@@133)	—	—	1	—	300	32	B	2(115),#29
					300	Note A	D	
VG (@@134)	26-14 Str/Sol	Cu	2	3.5	300	10	B, D	2(115),4,#30
OP (@@135)	—	—	1	—	300	10	B, D	2(115),#30

EQ (@@136)	12 - 22 Str/Sol	Cu	2	3.5	300	10	B, D	2(115), 4
EQ (@@136a)	12 - 30 Str/Sol	Cu	2	3.5	300	16	B, D	2(115), 4
YK301(@@137), YK302(@@137), YK303(@@137), YK304(@@137), YK305(@@137), YK306(@@137), YK301(@@138), YK302(@@138), YK303(@@138), YK304(@@138), YK305(@@138), YK306(@@138)	14 - 22 Str/Sol	Cu	2	5.2	300	15	B	2(115), 4
					300	Note A	D	
YK50A (@@139a)	10 - 22 Str/Sol	Cu	2	7	300	30	B	2(115), 4
					300	Note A	D	
YK50A (@@139b)	10 - 22 Str/Sol	Cu	2	7	300	30	B	2(125), 4
					300	Note A	D	
YK701 (@@139)	10 - 22 Str/Sol	Cu	2	13	300	30	B	2(115), 4
					300	Note A	D	
H7 (@@140)	16-20, Str/Sol	Cu	2	—	300	8	B, D	2(115), 4
H7 (@@141)	16-20, Str/Sol	Cu	2	—	300	8	B, D	2(115), 4

HX (@@142)	16-26, Str	Cu	2	—	300	8	B, D	2(115), 4
HX (@@143)	16-26, Str/Sol	Cu	2	—	300	8	B, D	2(115), 4
ES (@144)	14-30, SOL/STR	Cu	2	4.3	300	15	B	2(115), 4, Note 2
					300	Note A	D	
TJ(@145)	16-26, SOL/STR	Cu	2	2.5	300	10	B	2(115), 4, #31
VO(@146)	—	—	1	—	300	10	B	2(115), #31
EV (@@147)	6-20, SOL/STR	Cu	2	10.4	300	55	B, C	2(115), 4, #32
					600	Note A	D	
EV (@@231), EV (@@383)	6-20, SOL/STR	Cu	2	17.4	300	55	B, C	2(115), 4, #32
					600	Note A	D	
EW (@@148)	—	—	1	—	300	55	B, C	2(115), #32
					600	Note A	D	
YB09 (@@149)	14-24, SOL/STR	Cu	2	3.5	300	10	B	2(115), 4, Note 5
YB06 (@@150)	14-24, SOL/STR	Cu	2	3.5	300	10	B	2(115), 4, Note 4
VA (@@151)	22-14, Str/Sol	Cu	2	3.5	300	15	B	2 (115), 4, Note 2
					300	Note A	D	

T9 (@@152)	24-14, Str/Sol	Cu	2	3.2	300	15	B	2 (115), 4, Note 2
					300	Note A	D	
EN (@@153)	22-6, Str/Sol	Cu	2	13	300	57	B, C	2 (115), 4
					600	Note A	D	
EB (@@154)	22-12, Str/Sol	Cu	2	4.3	300	20	B	2 (115), 4, Note 7
					300	Note A	D	
TJ (@@155)	24-12, Str/Sol	Cu	2	5	300	20	B	2 (115), 4, #33
					300	Note A	D	
EU (@@156)	—	—	1	—	300	20	B	2 (115), #33
					300	Note A	D	
EJ (@@157)	18-3	Cu	2	30	600	100	B, C	2 (115), 4
EK (@@158), EK (@@232), EK (@@232a)	30-12	Cu	2	4.3	300	15	B	2 (115), 4, Note 2
					300	Note A	D	
TY (@@159), TY (@@159A)	26-14	Cu	2	3.5	300	10	B, D	2 (115), 4, #34
OP (@@160)	—	—	1	—	300	10	B, D	2 (115), #34
OP (@@160a)	—	—	1	—	300	10	B, D	2 (65), #34

FW (@@421), FW (@@422)	—	—	1	—	300	10	B, D	2 (120), #34
YK441 (@@161), YK441 (@@161a)	10-22, Str/Sol	Cu	2	10.54	300	30	B	2 (115), 4
					300	Note A	D	
YK442 (@@161)	10-22, Str/Sol	Cu	2	10.54	300	30	B	2 (115), 4
					300	Note A	D	
YK443 (@@161)	10-22, Str/Sol	Cu	2	10.54	300	30	B	2 (115), 4
					300	Note A	D	
YK444 (@@161)	10-22, Str/Sol	Cu	2	10.54	300	30	B	2 (115), 4
					300	Note A	D	
YK445 (@@161)	10-22, Str/Sol	Cu	2	10.54	300	30	B	2 (115), 4
					300	Note A	D	
YK446 (@@161)	10-22, Str/Sol	Cu	2	10.54	300	30	B	2 (115), 4
					300	Note A	D	
YK447 (@@161)	10-22, Str/Sol	Cu	2	10.54	300	30	B	2 (115), 4
					300	Note A	D	
YK511 (@@162)	10-22, Str/Sol	Cu	2	8.8	300	30	B	2 (115), 4
					300	Note A	D	
YK511 (@@163)	10-22, Str/Sol	Cu	2	8.8	300	30	B	2 (115), 4

					300	Note A	D	
YK512 (@@162)	10-22, Str/Sol	Cu	2	8.8	300	30	B	2 (115), 4
					300	Note A	D	
YK512 (@@163)	10-22, Str/Sol	Cu	2	8.8	300	30	B	2 (115), 4
					300	Note A	D	
YK513 (@@162)	10-22, Str/Sol	Cu	2	8.8	300	30	B	2 (115), 4
					300	Note A	D	
YK513 (@@163)	10-22, Str/Sol	Cu	2	8.8	300	30	B	2 (115), 4
					300	Note A	D	
YK514 (@@162)	10-22, Str/Sol	Cu	2	8.8	300	30	B	2 (115), 4
					300	Note A	D	
YK514 (@@163)	10-22, Str/Sol	Cu	2	8.8	300	30	B	2 (115), 4
					300	Note A	D	
YK515 (@@162)	10-22, Str/Sol	Cu	2	8.8	300	30	B	2 (115), 4
					300	Note A	D	
YK515 (@@163)	10-22, Str/Sol	Cu	2	8.8	300	30	B	2 (115), 4
					300	Note A	D	
YK551 (@@164)	10-22, Str/Sol	Cu	2	9.5	300	30	B	2 (115), 4

					300	Note A	D	
YK552 (@@164)	10-22, Str/Sol	Cu	2	9.5	300	30	B	2 (115), 4
					300	Note A	D	
YK553 (@@164)	10-22, Str/Sol	Cu	2	9.5	300	30	B	2 (115), 4
					300	Note A	D	
YK554 (@@164)	10-22, Str/Sol	Cu	2	9.5	300	30	B	2 (115), 4
					300	Note A	D	
YK555 (@@161)	10-22, Str/Sol	Cu	2	9.5	300	30	B	2 (115), 4
					300	Note A	D	
TO (@@166)	16-26, Str/Sol	Cu	2	3.5	300	10	B	2 (115), 4
TO (@@167)	16-26, Str/Sol	Cu	2	3.5	300	10	B	2 (115), 4
TO (@@167A)	16-26, Str/Sol	Cu	2	3.5	300	10	B	2 (115), 4
TO (@@167B)	16-26, Str/Sol	Cu	2	3.5	300	10	B	2 (115), 4
YK211 (@@168)	16-22, Str/Sol	Cu	2	6.5	300	10	B, D	2 (120), 4
YK31A (@@168)	14-22, Str/Sol	Cu	1	5.5	300	15	B	2 (120)
					300	Note A	D	
E2 (@@177)	28-14, STR/SOL	Cu	2	1.7	300	10	B, D	2 (115), 4, #35
EL (@@178)	—	—	1	—	300	10	B, D	2 (115), #35

EL (@@179)	—	—	1	—	300	10	B, D	2 (130), #35
V7 (@@180)	—	—	1	—	300	20	B	2 (115), #36
					300	Note A	D	
V7 (@@333)	—	—	1	—	300	12	B	2 (115), #36
					300	Note A	D	
V8 (@@181), V8 (@@181a)	24-12, STR/SOL	Cu	2	4	300	20	B	2 (115), 4, #36
					300	Note A	D	
V8 (@@334)	24-12, STR/SOL	Cu	2	4	300	12	B	2 (115), 4, #36
					300	Note A	D	
KI (@@334a)	20-18 AWG, STR (0.5-1.0 mm ² , STR)	Cu	2	—	300	8	B, D	2(115), 4, #36
	16-14 AWG, STR (1.5-2.5 mm ² , STR)	Cu	2	—	300	10	B, D	2(115), 4, #36
NA (@@182)	28-20, STR/SOL	Cu	2	—	150	3	B	2 (115), 4
HI (@@183)	28-12, STR/SOL	Cu	2	—	300	8	B, D	2 (115), 4, #37, #38
NB (@@184)	28-12, STR/SOL	Cu	2	—	300	8	B, D	2 (115), 4, #37

NC (@@185) NC (@@185A) NC (@@185B) NC (@@185C)	—	—	1	—	300	8	B, D	2 (115), #38
HL (@@186)	16-20, Solwith Push-In Type Connections	Cu	2	—	300	2	B, D	2(115), 4
HL (@@186)	AWM, Style 1015, 22, Solwith Insulation Displacement Connections	Cu	1	—	300	2	B, D	2(115)
VP (@@188), VP (@@384)	6-20, STR/SOL	Cu	2	19	300	65	B	2 (115), 4, Note 8
					300	Note A	D	
VP (@@189)	6-20, STR/SOL	Cu	2	19	300	65	B	2 (115), 4, Note 8
					600	Note A	D	
VP (@@190)	6-20, STR/SOL	Cu	2	19	300	65	B, C	2 (115), 4, Note 8
					600	Note A	D	
VP (@@191)	6-20, STR/SOL	Cu	2	19	600	65	B, C	2 (115), 4, Note 8
YK111, YK112, YK113, YK114 (@@192)	12-22, STR/SOL	Cu	2	11	300	20	B	2 (115), 4
YK11E03, YK11E04 (@@193)	12-22, STR/SOL	Cu	2	8.7	150	20	B	2 (115), 4

YK321 (@@194)	14-22, STR/SOL	Cu	1	5.2	300	15	B	2 (115)
					300	Note A	D	
YK61A (@@195)	12-22, STR/SOL	Cu	1	12	300	20	B	2 (115)
YK661 (@@196)	12-22, STR/SOL	Cu	2	7	300	15	B	2 (115), 4, #39
					300	Note A	D	
HB (@@199)	18-24, SOL/STR, two wires	Cu	2	—	300	10	B, D	2 (115), 4
HG (@@200)	12-28, SOL/STR	Cu	2	—	300	15	B	2 (115), 4
					300	Note A	D	
HG (@@407), HG (@@471)	12-28, SOL/STR	Cu	2	—	600	15	B, C	2 (115), 4
HT (@@201)	12-28, SOL/STR	Cu	2	—	300	15	B	2 (115), 4
					300	Note A	D	
HQ (@@202)	12-28, SOL/STR	Cu	2	—	300	10	B, D	2 (115), 4
HR (@@203)	12-28, SOL/STR	Cu	2	—	300	10	B, D	2 (115), 4
HW (@@204)	20-28, SOL/STR	Cu	2	—	150	4	B	2 (115), 4, #40
VL (@@205)	—	—	1	—	150	4	B	2 (115), #40
OQ (@@206)	—	—	1	—	150	4	B	2 (115), #40

OQ (@@206A)	—	—	1	—	150	4	B	2 (65), #40
OQ (@@206B)	—	—	1	—	150	4	B	2 (130), #40
HW (@@207)	16-28, SOL/STR	Cu	2	—	300	8	B	2 (115), 4, #40
VL (@@208)	—	—	1	—	300	8	B	2 (115), #40
VM (@@209)	28-16, SOL/STR	Cu	2	1.7	300	10	B	2 (115), 4, #41
VL (@@210)	—	—	1	—	300	10	B	2 (115), #41
HA (@@211)	26-16, SOL/STR	Cu	2	—	300	6	B, D	2 (115), 4
NE (@@212)	20-16, SOL	Cu	2	—	300	10	B, D	2 (115), 4
NE (@@213)	20-16, SOL	Cu	2	—	300	10	B, D	2 (115), 4
KD (@@214), KD (@@214b)	24-16, SOL/STR	Cu	2	—	160	5.5	B, D	2 (115), 4, #42
KE (@@215)	—	—	1	—	160	5.5	B, D	2 (115), #42
KE (@@215a)	—	—	1	—	160	5.5	B, D	2 (130), #42
OQ (@@213a)	—	Cu	1	—	300	15	B, D	2(115), #13
OQ (@@216)	—	Cu	1	—	125	4	B, D	2(115), #13
OQ (@@214a)	—	Cu	1	—	300	10	B, D	2(115), #13
VM (@@224), (@@335), (@@336)	12-22, SOL/STR	Cu	2	3.5	300	20	B	2 (115), 4, #43
					300	Note A	D	

VM (@@337), (@@338), (@@456)	12-22, SOL/STR	Cu	2	3.5	300	12	B	2 (115), 4, #43
					300	Note A	D	
OQ (@@225)	—	—	1	—	300	20	B	2 (115), #43
					300	Note A	D	
OQ (@@339), (@@340) (@@457)	—	—	1	—	300	12	B	2 (115), #43
					300	Note A	D	
EZ (@@226)	12-22, SOL/STR	Cu	2	4.3	300	15	B	2 (115), 4, #44
OQ (@@227)	—	—	1	—	300	20	B	2 (115), #43, #44
OQ (@@228)	—	—	1	—	300	20	B	2 (115), #43, #44
VR (@@229) VR (@@229A) VR (@@229B)	14-30, SOL/STR	Cu	2	2	300	10	B, D	2 (115), 4, #45
VS (@@230) VS (@@230A) VS (@@230D) VS (@@230E)	—	—	1	—	300	10	B, D	2 (115), #45
VS (@@230B) VS (@@230C)	—	—	1	—	300	10	B, D	2 (130), #45
E4 (@@233)	26-10, STR/SOL	Cu	2	9	300	30	B	2 (105), 4
					300	Note A	D	
TZ (@@234)	30-14, STR/SOL	Cu	2	3.5	300	6	B	2 (130), 4

TZ (@@235)	30-14, STR/SOL	Cu	2	3.5	300	6	B	2 (130), 4
H8 (@@236)	24-6, STR/SOL	Cu	2	—	300	37	B	2 (105), 4
					300	Note A	D	
H8 (@@237)	24-6, STR/SOL	Cu	2	—	600	37	B, C	2 (105), 4
H8 (@@237a)	24-6	Cu	2	—	600	57	B, C	2(105), 4
H4 (@@238)	26-12, STR/SOL	Cu	2	—	300	10	B, D	2 (105), 4, #46
VF (@@239)	—	—	1	—	300	10	B, D	2 (105), #46
V7 (@@240)	—	—	1	—	300	4	B	2 (105), #47
H5 (@@241)	28-16, STR/SOL	Cu	2	—	300	4	B	2 (105), 4, #47
V7 (@@242)	—	—	1	—	300	4	B, D	2 (105), #48
H5 (@@243)	28-16, STR/SOL	Cu	2	—	300	4	B, D	2 (105), 4, #48
V7 (@@244), V7 (@@244a)	—	—	1	—	300	10	B, D	2 (105), #49
H5 (@@245), H5 (@@245a)	26-12, STR/SOL	Cu	2	—	300	10	B, D	2 (105), 4, #49
YA (@@273)	24-16, STR/SOL	Cu	2	1.7	150	10	B	2 (115), 4
KQ (@@274)	22-6, STR/SOL	Cu	2	19	300	64	B, C	2 (115), 4
					300	Note A	D	

KH (@@275)	24-10, STR/SOL	Cu	2	4.3	300	30	B	2 (115), 4
					300	Note A	D	
KR (@@276), (@@277)	26-14, STR/SOL	Cu	2	3.5	300	10	B, D	2 (115), 4, #50
OP (@@278), (@@279)	—	—	1	—	300	10	B, D	2 (115), #50
OP (@@279A) OP (@@279B)	—	—	1	—	300	10	B, D	2 (65), #50
KK (@@280)	20-6, STR/SOL	Cu	2	18	300	55	B	2 (115), 4, #51
					300	Note A	D	
KL (@@281)	—	—	1	—	300	55	B	2 (115), #51
					300	Note A	D	
HX (@@290)	16-26, STR/SOL	Cu	2	—	300	10	B	2(115), 4
KO (@@295)	24-10, STR/SOL	Cu	2	5.5	300	30	B, C	2 (115), 4
					600	Note A	D	
KO (@@296)	24-10, STR/SOL	Cu	2	5.5	600	30	B, C	2 (115), 4
					600	Note A	D	
YH (@@297)	28-12, STR/SOL	Cu	2	4.3	300	20	B	2 (115), 4
					300	Note A	D	

YK90 (@@298)	10-6, STR/SOL	Cu	2	26	600	65	B, C	2 (115), 4,5
					600	Note A	D	
	Two wires, 10-6, STR/SOL	Cu	2	26	600	65	B, C	2(115), 5
					600	Note A	D	
TJ (@@299)	26-16, STR/SOL	Cu	2	2.3	300	10	B	2 (115), 4, #52
VF (@@300)	—	—	1	—	300	10	B	2 (115), #52
HW (@@301)	26-12, STR/SOL	Cu	2	—	300	10	B, D	2 (115), 4, #53
OQ (@@302), OQ (@@303)	—	—	1	—	300	10	B, D	2 (115), #53
TR (@@306)	26-16, STR/SOL	Cu	2	2	300	8	B, D	2 (115), 4
VQ (@@307) (@@308)	30-16, STR/SOL	Cu	2	1.7	300	10	B	2 (115), 4
KP (@@309)	24-10, STR/SOL	Cu	2	5.3	300	30	B	2 (115), 4
					300	Note A	D	
KP (@@310)	24-10, STR/SOL	Cu	2	5.3	600	30	B, C	2 (115), 4
					600	Note A	D	
KP (@@311), KP (@@311a)	20-6, STR/SOL	Cu	2	12.2	300	65	B	2 (115), 4
					300	Note A	D	

KP (@@312), KP (@@312a)	20-6, STR/SOL	Cu	2	12.2	600	65	B, C	2 (115), 4
					600	Note A	D	
HW (@@313)	28-14, STR/SOL	CU	2	—	300	8	B	2 (115), 4, #54
V5 (@@314)	28-14, STR/SOL	Cu	2	2.17	300	8	B	2 (115), 4, #54
YK881 (@@315)	18-8, STR/SOL	Cu	2	16	600	45	B, C	2 (120), 4, 5
	Two wires, 18-8, STR/SOL	Cu	2	16	600	45	B, C	2(120), 5
VW (@@316)	28-18, STR/SOL	Cu	2	—	150	7	B	2 (115), 4, #55
VX (@@317), VX (@@317a)	—	—	1	—	150	10	B	2 (115), #55
VX (@@317b), VX (@@317c)	—	—	1	—	150	10	B	2 (130), #55
N4 (@@513)	16-30	Cu	2	—	300	10	B, D	2 (120), 4, #55
TE (@@318), (@@319)	26-16, STR/SOL	Cu	2	1.7	125	10	B	2 (115), 4
YK70A (@@341)	18-8, Sol/Str	Cu	1	16	300	40	B,C	2(120), 5
					600	Note A	D	
DS-240 (@@342)	16-28, STR/SOL	Cu	2	—	300	10	B, C, D	2(115), 4
KD (@@343)	16-24, STR/SOL	Cu	2	—	300	5.5	B, D	2(115), 4, #56
KD (@@343a)	16-24, STR/SOL	Cu	2	—	300	8	B, D	2(115), 4, #56
KD (@@343b)	16-24, STR/SOL	Cu	2	—	300	8	B, D	2(115), 4, #56

KE (@@344)	—	—	1	—	300	8	B, D	2(115), #56
KE (@@344a)	—	—	1	—	300	8	B, D	2(115), #56
KE (@@344b)	—	—	1	—	300	8	B, D	2(130), #56
OQ (@@344c)	—	—	1	—	300	8	B, D	2(120), #56
KD (@@345)	14-24, STR/SOL	Cu	2	—	300	12	B	2(115), 4, #56KD, #56a
					300	Note A	D	
KE (@@346), KE (@@346a)	—	—	1	—	300	12	B	2(120), #56
					300	Note A	D	
TX (@@347)	14-26, SOL/STR	Cu	2	3.9	300	10	B	2 (115), 4, #57
EX (@@348)	—	—	1	—	300	10	B	2 (115), #57
YC (@@349)	16-26, SOL/STR	Cu	2	3.0	300	10	B	2 (115), 4
YT (@@350)	12~24, SOL/STR	Cu	2	3.5	300	10	B, D	2 (115), 4
KX (@@351), (@@352)	20-2	Cu	2	31.5	600	115	B, C	2 (120), 4, #58
KU (@@353), (@@354)	—	—	1	—	600	115	B, C	2 (120), #58
YK66A (@@355)	26-16, STR/SOL	Cu	2	5.2	300	10	B, D	2(130), 4
YK711 (@@356)	20-10, STR/SOL	Cu	2	15	300	30	B	2(130), 4

					150	30	C	
					300	Note A	D	
KJ (@@357)	20-6, STR/SOL	Cu	2	18	600	55	B, C	2 (120), 4, #59
KK (@@358)	20-6, STR/SOL	Cu	2	18	600	55	B, C	2 (120), 4, #59
H6 (@@385)	12~20, STR/SOL	Cu	2	—	300	11	B	2(115), 4
						Note A	D	
H6 (@@386)	12~20, STR/SOL	Cu	2	—	300	11	B	2(115), 4
						Note A	D	
H6 (@@387)	12~20, STR/SOL	Cu	2	—	300	11	B	2(115), 4
						Note A	D	
ND (@@388)	14~26, STR/SOL	Cu	2	—	300	10	B, D	2(115), 4
ND (@@389)	14~26, STR/SOL	Cu	2	—	300	10	B, D	2(115), 4
HP (@@390)	Style 1015, 20~22, STR/SOL	Cu	2	—	300	5	B, D	2(115), 4, #60
VZ (@@391)	—	—	1	—	300	5	B, D	2(115), #60
V8 (@@392)	14~30, SOL/STR	Cu	2	2.6	300	8	B	2 (115), 4, #61
V7 (@@393)	—	—	1	—	300	8	B	2 (115), #61

V9 (@@394)	12~30, SOL/STR	Cu	2	5.2	300	12	B	2 (115), 4, #62
						Note A	D	
VZ (@@395)	—	—	1	—	300	12	B	2 (115), #62
						Note A	D	
KI (@@395a)	20-18 AWG, STR (0.5-1.0 mm ² , STR)	Cu	2	—	300	7	B, D	2(115), 4, #61
TJ (@@396)	30-12, STR/SOL	Cu	2	4.4	300	12	B	2 (115), 4 #63
					300	Note A	D	
V5 (@@397)	30-12, STR/SOL	Cu	2	4.4	300	12	B	2 (115), 4, #63
					300	Note A	D	
ET (@@398), (@@399)	24-8, STR/SOL	Cu	2	9	600	4	B, C	2 (115), 4, #64
					600	Note A	D	
KT (@@400), (@@401)	24-8, STR/SOL	Cu	2	9	600	41	B, C	2 (115), 4, #64
					600	Note A	D	
HS (@@402), (@@403), (@@404)	28-12, STR/SOL	Cu	2	—	300	10	B, D	2 (115), 4
YK66B(@@406)	16-26, STR/SOL	Cu	2	5.2	300	10	B, D	2 (120), 4

KY (@@408)	24-12, STR/SOL	Cu	2	3	300	15	B	2 (115), 4
					300	Note A	D	
NM (@@409)	18-24, SOL	Cu	2	—	300	7	B, D	2 (75), 4
	16-22, STR	Cu	2	—	300	10	B, D	2 (75), 4
NM (@@410)	18-24, SOL	Cu	2	—	300	7	B	2 (75), 4
	16-22, STR	Cu	2	—	300	10	B	2 (75), 4
NM (@@410a)	18-24, SOL	Cu	2	—	300	7	B, D	2 (130), 4
	16-22, STR	Cu	2	—	300	10	B, D	2 (130), 4
NM (@@410b)	18-24, SOL	Cu	2	—	300	7	B	2 (130), 4
	16-22, STR	Cu	2	—	300	10	B	2 (130), 4
E7 (@@411)	22-14, STR/SOL	Cu	2	3.5	300	15	B	2(115), 4
					300	Note A	D	
E7 (@@412)	22-14, STR/SOL	Cu	2	3.5	300	15	B, C	2(115), 4
K6 (@@413)	24-16, STR/SOL	Cu	2	2.7	300	10	B	2(115), 4
K6 (@@414)							B, D	
E3 (@@483)	26-14, STR/SOL	Cu	2	1.7	125	10	B, D	2(115), 4
E6 (@@415)	30-12, STR/SOL	Cu	2	5	300	10	B, D	2(115), 4

E9 (@@415a)	6-20, STR/SOL	Cu	2	15.6	1000	65	E	2(115), 4
NH (@@416)	26-16, STR/SOL	Cu	2	—	300	10	B, D	2(115), 4
KZ (@@417)	26-12, STR/SOL	Cu	2	2.4	300	15	B	2(115), 4
					300	Note A	D	
KZ (@@418)	26-12, STR/SOL	Cu	2	3.5	300	15	B	2(115), 4
					300	Note A	D	
KZ (@@419)	26-12, STR/SOL	Cu	2	2.4	300	15	B, C	2(115), 4
KZ (@@420)	26-12, STR/SOL	Cu	2	3.5	300	15	B, C	2(115), 4
TV (@@423)	30-16, STR/SOL	Cu	2	3.5-5.3	300	10	B	2(115), 4
	14, STR/SOL	Cu	2	3.5	300	10	B	2(115), 4
TV (@@424), TV (@@424a), TV (@@424b)	30-16, STR/SOL	Cu	2	3.5-5.3	300	10	B, D	2(115), 4
	14, STR/SOL	Cu	2	3.5	300	10	B, D	2(115), 4
NK (@@430)	24-8, Str	Cu	2	—	300	35	B	2(120), 4
					150	35	C	
					600	Note A	D	
	24-10, Sol	Cu	2	—	300	30	B	2(120), 4
					150	30	C	

					600	Note A	D	
NK (@@431)	24-8, Str	Cu	2	—	300	35	B, C	2(120), 4
					600	Note A	D	
	24-10, Sol	Cu	2	—	300	30	B, C	2(120), 4
					600	Note A	D	
KT (@@432), KT (@@433)	24-8, STR/SOL	Cu	2	9	300	41	B, C	2 (115), 4, #65
					600	Note A	D	
KS (@@434)	—	—	1	—	300	41	B, C	2 (115), #65
					600	Note A	D	
KZ (@@435)	26-16, STR/SOL	Cu	2	1.1	300	10	B, D	2(115), 4
NJ (@@436)	24-16, Sol/Str	Cu	2	—	300	10	B, D	2(115), 4
NJ (@@437)	24-12, Str	Cu	2	—	300	16	B	2(115), 4
					300	Note A	D	
	24-14, Sol	Cu	2	—	300	13	B	2(115), 4
					300	Note A	D	
NJ (@@517)	24-16, Sol/Str	Cu	2	—	300	10	B, D	2(115), 4
NJ (@@517)	24-12, Str	Cu	2	—	300	16	B	2(115), 4

					300	Note A	D	
	24-14, Str	Cu	2	—	300	13	B	2(115), 4
					300	Note A	D	
NI (@@438), NI (@@484)	16-26, Sol/Str	Cu	2	—	300	10	B	2(115), 4
NI (@@439), NI (@@485)	16-26, Sol/Str	Cu	2	—	300	10	B	2(115), 4
							D	
HN (@@440)	26-14, Sol/Str	Cu	2	—	300	10	B, D	2 (115), 4, #66
EL (@@441)	—	—	1	—	300	10	B, D	2 (115), #66
EL (@@441a)	—	—	1	—	300	10	B, D	2 (130), #66
NP (@@442)	4-20, Str	Cu	2	—	300	40	B	2(120), 4
					300	Note A	D	
	8-20, Sol	Cu	2	—	300	30	B	2(120), 4
					300	Note A	D	
NP (@@443)	4-20, Str	Cu	2	—	600	40	B, C	2(120), 4
	8-20, Sol	Cu	2	—	600	30	B, C	2(120), 4
NF (@@444)	26-12, Sol/Str	Cu	2	—	300	12	B, D	2 (115), 4, #67
OQ (@@445)	—	—	1	—	300	12	B, D	2 (115), #67
ET (@@446)	24-8, SOL/STR	Cu	2	11.4	300	41	B, D	2(115), 4, #68

					150	41	C	
ET (@@447)	24-8, SOL/STR	Cu	2	11.4	300	41	B, D	2(115), 4, #68
					150	41	C	
VC (@@448)	—	—	1	—	300	41	B	2(115), #68
						Note A	D	
VC (@@449)	—	—	1	—	300	41	B	2(115), #68
						Note A	D	
VC (@@449a)	—	—	1	—	300	41	B, D	2(115), 4, 7(III, 0.216/5.5, 0.315/8), #68
					150	41	C	
					600	41	F	
WR018 (@@449b)	24-8	Cu	2	—	600	35	B, C	2(115), 4, #68
WR01800 (@@449c) (For WR018 terminals)	24-8	Cu	2	—	600	35	B, C	2(115), 4, #68
WR01801 (@@449c) (For WR018 terminals)	24-8	Cu	2	—	600	35	B, C	2(115), 4, #68
WR01800 (@@449c) (For KD terminals)	24-16, SOL/STR	Cu	2	—	300	8	B, D	2(115), 4, #68
WR01801 (@@449c) (For KD terminals)	24-16, SOL/STR	Cu	2	—	300	8	B, D	2(115), 4, #68
K8 (@@450)	28-16 STR/SOL	Cu	2	1.7~2.0	300	8	B	2 (115), 4, #69

VE (@@451)	—	—	1	—	300	8	B	2 (115), #69
K8 (@@452)	28-16 STR/SOL	Cu	2	1.7~2.0	300	8	B, D	2 (115), 4, #69
VE (@@453)	—	—	1	—	300	8	B, D	2 (115), #69
K9 (@@454)	20-1/0	Cu	2	34~36.5	600	127	B, C	2 (120), 4
					600	Note A	D	
K9 (@@454a)	20-1	Cu	2	49	600	160	B, C	2 (115), 4
NS (@@455)	18-22, SOL	Cu	2	—	150	7	B, D	2 (115), 4
NT (@@460a)	18-24, Sol/Str, AWM, Style 1015	Cu	2	—	300	5	B, D	2(115), 4, #70
NT (@@460b)	18-24, Sol/Str, AWM, Style 1015	Cu	2	—	300	5	B	2(115), 4, #70
					600	5	D	
OQ (@@461a)	—	—	1	—	300	5	B, D	2(120), #70
OQ (@@461b)	—	—	1	—	300	5	B	2(120), #70
					600	5	D	
NP (@@462a)	4-20, Str, 8-20, Sol	Cu	2	—	300	50	B	2(120), 4
						Note A	D	
NP (@@462b)	4-20, Str	Cu	2	—	600	50	B, C	2(120), 4

	8-20, Sol	Cu	2	—				
NP (@@462c)	4-20, Str 8-20, Sol	Cu	2	—	300	45	B	2(120), 4
						Note A	D	
NX (@@463a)	24-16, STR/SOL	Cu	2	—	300	7	B, D	2 (115), 4
NX (@@463b)	24-16, STR/SOL	Cu	2	—	300	7	B, C, D	2 (115), 4
HM (@@464)	28-14, STR/SOL	Cu	2	—	300	8	B	2 (115), 4
TZ (@@465)	16-30, Sol/Str	Cu	2	1.7	300	10	B	2(110), 4
TZ (@@466)							B, D	
NV (@@467)	24-16, STR/SOL	Cu	2	—	300	5.5	B, C, D	2 (115), 4, #71
NL (@@467)	24-16, STR/SOL	Cu	2	—	300	5.5	B, C, D	2 (115), 4, #71
NV (@@468)	24-16, STR/SOL	Cu	2	—	300	5.5	B, C, D	2 (115), 4, #71
NL (@@468)	24-16, STR/SOL		2	—	300	5.5	B, C, D	2 (115), 4, #71
NV (@@468a)	24-16, STR/SOL	Cu	2	—	300	8	B, C, D	2 (115), 4, #71

NL (@@468a)	24-16, STR/SOL	Cu	2	—	300	8	B, C, D	2 (115), 4, #71
NV (@@468b)	24-16, STR/SOL	Cu	2	—	300	8	B, C, D	2 (115), 4, #71
NL (@@468b)	24-16, STR/SOL		2	—	300	8	B, C, D	2 (115), 4, #71
NV (@@468c)	24-16, STR/SOL	Cu	2	—	300	5.5	B, C, D	2 (115), 4, #71
NL (@@468c)	24-16, STR/SOL	Cu	2	—	300	5.5	B, C, D	2 (115), 4, #71
NV (@@468d)	24-16, STR/SOL	Cu	2	—	300	5.5	B, C, D	2 (115), 4, #71
NL (@@468d)	24-16, STR/SOL		2	—	300	5.5	B, C, D	2 (115), 4, #71
NV (@@468e)	24-16, STR/SOL	Cu	2	—	300	8	B, C, D	2 (115), 4, #71
NL (@@468e)	24-16, STR/SOL	Cu	2	—	300	8	B, C, D	2 (115), 4, #71
NV (@@468f)	24-16, STR/SOL	Cu	2	—	300	8	B, C, D	2 (115), 4, #71

NL (@@468f)	24-16, STR/SOL	Cu	2	—	300	8	B, C, D	2 (115), 4, #71
NW (@@469)	—	—	1	—	300	8	B, D	2 (130), #71
NR (@@469)	—	—	1	—	300	8	B, D	2 (130), #71
NW (@@470)	—	—	1	—	150	8	B	2 (130), #71
NR (@@470)	—	—	1	—	150	8	B	2 (130), #71
NW (@@470a)	—	—	1	—	300	8	B, D	2 (130), #71
NR (@@470a)	—	—	1	—	300	8	B, D	2 (130), #71
NW (@@470b)	—	—	1	—	150	8	B	2 (130), #71
NR (@@470b)	—	—	1	—	150	8	B	2 (130), #71
NW (@@470c)	—	—	1	—	300	8	B	2 (120), #71
NR (@@470c)	—	—	1	—	300	8	B	2 (120), #71
NW (@@470d)	—	—	1	—	150	8	B	2 (120), #71
NR (@@470d)	—	—	1	—	150	8	B	2 (120), #71
NW (@@470e)	—	—	1	—	300	8	B	2 (120), #71
NR (@@470e)	—	—	1	—	300	8	B	2 (120), #71
NW (@@470f)	—	—	1	—	150	8	B	2 (120), #71
NR (@@470f)	—	—	1	—	150	8	B	2 (120), #71
NW (@@470g)	—	—	1	—	150	8	B	2 (120), #71
NR (@@470g)	—	—	1	—	150	8	B	2 (120), #71
NW (@@470h)	—	—	1	—	150	8	B	2 (120), #71

NR (@@470h)	—	—	1	—	150	8	B	2 (120), #71
NW (@@470i)	—	—	1	—	150	8	B	2 (130), #71
NR (@@470i)	—	—	1	—	150	8	B	2 (130), #71
NW (@@470j)	—	—	1	—	150	8	B	2 (130), #71
NR (@@470j)	—	—	1	—	150	8	B	2 (130), #71
WR-03 series / WR003 (@@472)	26-16, Sol/Str	Cu	2	1.77-2.21	300	10	B	2(115), 4
	24-20, Str	Cu	2	1.77-2.21	300	8	B	2(115), 5
	(2)24-20, Str	Cu	2	1.77-2.21	300	8	B	2(115), 4
YK66D (@@473)	16-26, Sol/Str	Cu	2	5.2	300	10	B, D	2(130), 4
WR013 (@@476)	1/0~4	Cu	2	57	600	150	B, C	2 (130), 5
YK44B (@@477)	12-22, Sol/Str	Cu	2	12	300	20	B	2(140), 4
					300	Note A	D	
YK44B (@@477a)	12-22, Sol/Str	Cu	2	12	300	20	B	2(130), 4
					300	Note A	D	
YK50B (@@477)	8-22, Sol/Str	Cu	2	12 - 16	300	35	B	2(130), 5
					300	Note A	D	
NZ (@@478)	6-16, Sol/Str	Cu	2	—	300	55	B	2(115), 4
					300	Note A	D	

NZ (@@479)	6-16, Sol/Str	Cu	2	—	600	65	B, C	2(115), 4
NZ (@@479a)	10-24, STR/SOL	CU	2	—	600	30	B, C, D	2(115), 4
NZ (@@479b)	10-24, STR/SOL	CU	2	—	300	30	B, D	2(115), 4
					150	30	C	
WQ0003 (@@480), WQ0003 (@@481)	16-24, Sol/Str	Cu	2	—	150	2	B	2 (65), 4
YJ100 0310	8AWG - 1/0 Prepared Cond	Cu	2	38.9	600	74	B,C	2(120),5
YJ100 0321	8AWG - 1/0 Prepared Cond	Cu	2	69.0	600	114	B,C	2(120),5
YJ100 0331	8AWG - 1/0 Prepared Cond	Cu	2	69.0	600	140	B,C	2(120),5
WS0001 (@@482)	6-8	Cu	2	17.4	150	40	B, C	2(130), 5
					150	Note A	D	
WS006 (@@516)	12-22	Cu	2	12	300	10	B, C	2(125), 4, (#3)
					600	Note A	D	
NU (@@486), NU (@@487)	20-26, SOL	Cu	2	—	300	2	B	2(115), 4, #72
OP (@@488), OP (@@489)	—	—	1	—	300	2	B	2(130), #72
WS002 (@@490), WS002 (@@491)	12-22, SOL/STR	Cu	2	—	300	10	B, D	2(115), 4
NY (@@493), NY (@@494)	16-22, SOL/STR	Cu	2	—	150	2	B	2(115), 4, #73
OL (@@495), OL (@@496)	—	—	1	—	150	2	B	2(120), #73

EF (@@497)	12-30, SOL/STR	Cu	2	4.3-5.2	300	20	B, D	2(115), 4
WR015 (@@498), WR019 (@@499)	14-8, SOL/STR	Cu	2	13	600	30	B, C	2(140), 4
	14-8, STR	Cu	2	13	600	30	B, C	2(140), 5
	(2)14-8, STR	Cu	2	13	600	30	B, C	2(140), 5
WR026 (@@514), WR026 (@@515)	14-6	Cu	2	7-8.5	300	30	B, C	2(140), 5
					600	Note A	D	
KD (@@500)	26-20	Cu	2	—	150	6	B	2(115), 4, #74
			1		50	6	C	
OQ (@@501)	—	—	1	—	150	6	B	2(120), #74
					50	6	C	
OQ (@@502)	—	—	1	—	150	6	B	2(130), #74
					50	6	C	
WB0003 (@@503)	24-18, SOL	Cu	2	—	300	6	B, D	2(115), 4, #75
OP (@@504)	—	—	1	—	300	6	B, D	2(130), #75
OP (@@505)	—	—	1	—	300	6	B, D	2(65), #75
XC (@@506)	16-26, SOL/STR	Cu	2	1.7	300	10	B	2(115), 4
TW (@@507)	10-22, SOL/STR	Cu	2	4.4	300 (#)	30	B, D	2(120), 4
					150 (#)		C	

HO (@@508)	14-18, SOL	Cu	2	—	300	13	B, D	2(140), 4, #77
	14-18, STR	Cu	2	—	300	15	B, D	2(140), 4, #77
PD (@@508)	—	—	1	—	300	15	B, D	2(140), #77
XA (@@509)	10-24, SOL/STR	Cu	2	—	600	30	B, C, D	2(115), 4
XA (@@510)	10-24, SOL/STR	Cu	2	—	300	30	B, D	2(115), 4
XA (@@511)	10-24, SOL/STR	Cu	2	—	300	30	B, D	2(115), 4
					150	30	C	
N6 (@@512)	10-24	Cu	2	—	600	30	B,C,D	2(115), 4
WR021 (@@518)	12-6, SOL/STR	CU	2	40-44	600	65	B, C	2(140), 4
	(2)12-6, SOL/STR	CU	2	40-44	600	105	B, C	2(140), 4
	4-2, Str	CU	2	40-44	600	105	B, C	2(140), 5

Note: A - These limited ratings are applicable to a terminal block for use in or with industrial control equipment whereby the load on any single circuit of the terminal block does not exceed 15 A at 51-150 V, or 10 A at 151-300 V, or the maximum ampere rating, whichever is less.

Note 1 - The terminal blocks are constructed end to end stackable design, which may be assembled 3 thru 24 poles. The suitability of the assembly shall be determined in the end-use investigation.

Note 2 - The terminal blocks are constructed end to end stackable design, which may be assembled 4 thru 24 poles. The suitability of the assembly shall be determined in the end-use investigation.

Note 3 - The terminal blocks are constructed end to end stackable design, which may be assembled 8 thru 48 poles. The suitability of the assembly shall be determined in the end-use investigation.

Note 4 - The terminal blocks are constructed end to end stackable design, which may be assembled 12 thru 72 poles. The suitability of the assembly shall be determined in the end-use investigation.

Note 5 - The terminal blocks are constructed end to end stackable design, which may be assembled 18 thru 72 poles. The suitability of the assembly shall be determined in the end-use investigation.

Note 6 - The terminal blocks are constructed end to end stackable design, which may be assembled 5 thru 24 poles. The suitability of the assembly shall be determined in the end-use investigation.

Note 7 - The terminal blocks are constructed end to end stackable design, which may be assembled 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48 poles. The suitability of the assembly shall be determined in the end-use investigation.

Note 8 - The terminal blocks are constructed end to end stackable design, which may be assembled 4 thru 12 poles. The suitability of the assembly shall be determined in the end-use investigation.

(1) Followed by -A thru -E, followed by -4 thru -28, followed by P.

(2) Followed by 1 or 2, followed by -4 thru -31, followed by P.

(3) Followed by 1 thru 4, followed by -4 thru -31, followed by P.

(4) Followed by 1 thru 3, followed by -2 thru -30, followed by P.

(5) Followed by 1 thru 4, followed by -4 thru -30, followed by P.

(6) Followed by 1 thru 4, followed by -2 thru -30, followed by P.

(7) Followed by 1 thru 5, followed by -4 thru -32, followed by P.

(8) Followed by 1 thru 5, followed by -4 thru -28, followed by P.

(9) Followed by 1 thru 5, followed by -4 thru -32, followed by P.

(10) Followed by 1 thru 5, followed by -4 thru -30, followed by P.

(11) Followed by 1 or 2, followed by -4 thru -26, followed by P.

(12) Followed by 1 thru 4, followed by -4 thru -32, followed by P.

(13) Followed by 1 thru 6, followed by -2 thru -30, followed by P.

(14) Followed by 1 thru 4, followed by -4 thru -28, followed by P.

(15) Followed by 1, followed by -6, -10, -12, -20 or -30, followed by P.

(+) Followed by 03, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, may be followed by one digit.

(@1) Followed by 02 thru 30, followed by 02 or 03, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 2, followed by A, may be followed by one digit.

(@1a) followed by 02 or 03, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by one alphanumeric digit or blank, followed by four alphanumeric digits or blank, followed by F, G or H or blank.

(@2) Followed by 02 or 03, followed by 0 or 1, followed by 0, 1, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, may be followed by one digit.

- (@3) Followed by 02, 03 or 04, followed by 0 or 1, followed by 2 thru 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, may be followed by one digit.
- (@4) Followed by 02 or 03, followed by 2 or 3, followed by 2 thru 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, may be followed by one digit.
- (@5) Followed by 02, 04 or 06, followed by 0 or 1, followed by 0, 1, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, may be followed by one digit.
- (@6) Followed by 02, 03 or 04, followed by 0 or 1, followed by 0 thru 5, followed by 0, 5, 6 or 8, followed by 0 or 1.
- (@7) Followed by 02, 03 or 04, followed by 0 or 1, followed by 0 thru 5, followed by one digit, followed by 0.
- (@8) Followed by 03 or 06, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by one alphanumeric digit or blank, followed by 0 or blank, followed by four alphanumeric digits or blank, followed by F, G, H or blank.
- (@9) Followed by 01 or 02, followed by 3, followed by 0 or 1, followed by 0, 5, 6, 8 or C, followed by 0, 1 or 2, followed by four alphanumeric digits or blank, followed by F, G, H or blank.
- (@9a) Followed by 03 or 04, followed by 2, followed by 0 or 1, followed by 0, 5, 6, 8 or C, followed by 0, 1 or 2, followed by four alphanumeric digits or blank, followed by F, G, H or blank.
- (@10) Followed by 01, 02 or 03, followed by 0 thru 3, followed by 0 or 1, followed by 0, 5, 6 or 8, may be followed by one digit.
- (@11) Followed by 02 thru 24, followed by 0 or 5 thru 9, followed by 0, 1, 6 or 7, followed by 0, 5, 6, 8, 9, C or D, followed by 0, 2 or 3, followed by 0000, followed by G or H.
- (@12) Followed by 01, 02 or 03, followed by 0 thru 3, followed by 0 thru 5, followed by 0, 5, 6 or 8, followed by 0.
- (##1) Followed by 02 thru 30, followed by 0 or 3, followed by 0 thru 3, followed by one alphanumeric digits, followed by F, G, H or blank. Or Followed by 02 through 30, followed by 0 or 3, followed by 0 through 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (##1a) Followed by 02 through 30, followed by 3, followed by 0 through 3, followed by 2 or 3, followed by two alphanumeric digits, followed by F, G or H.
- (##2) Followed by 02 thru 31, followed by 0 thru 3, followed by 0 thru 3, followed by one or three alphanumeric digits, followed by F, G, H or blank.
- (##3) Followed by 02 thru 32, followed by 0 thru 3, followed by 0 thru 3, followed by one or three alphanumeric digits, followed by F, G, H or blank.
- (@@1) Followed by 02 thru 24, followed by 0 thru 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@2) Followed by 02 thru 30, followed by 2 or 3, followed by 0 thru 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@3) Followed by 01 thru 99, followed by 0 thru 4 or 6, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by two or four alphanumeric digits, followed by F, G, H or blank.
- (@@4) Followed by 02 thru 20, followed by 3 or 4, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0, followed by two or four alphanumeric digits, followed by F, G, H or blank.
- (@@5) Followed by 02 or 03, followed by 0, 2, 4 or 6, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@6) Followed by 02 thru 24, followed by 3, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits or blank, followed by F, G, H or blank.

(@@7) Followed by 02 thru 24, followed by 3, followed by 0, 1, 2, A, B or C, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits or blank, followed by F, G, H or blank.

(@@7A) Followed by 02 through 24, followed by 3, followed by D, E or F, followed by 0, followed by 0 or 1, followed by four alphanumeric digits or blank, followed by F, G, H or blank.

(@@7B) Followed by 02 through 12, followed by 4, followed by 0, 1, 2, A, B or C, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits or blank, followed by F, G, H or blank.

(@@7C) Followed by 02 through 12, followed by 4, followed by D, E or F, followed by 0, followed by 0 or 1, followed by four alphanumeric digits or blank, followed by F, G, H or blank.

(@@8) Followed by 01 thru 30, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8 9 or A thru M, followed by 0 thru 3, followed by two alphanumeric digits or blank.

(@@9) Followed by 02 thru 24, followed by 1 or 3, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0, 2 or 3, followed by 0 thru 4, followed by 0000 or three alphanumeric digits, followed by G, H, Z or blank.

(@@10) Followed by 02 thru 24, followed by 1 thru 4, followed by 1, 2 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9, C or D, followed by 0 or 1, followed by four alphanumeric digit, followed by G, H, F or blank, followed by Z or blank.

(@@10A) Followed by 02 through 24, followed by 1 or 3, followed by B or C, followed by 0, 1, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@10B) Followed by 02 through 24, followed by 1 or 3, followed by E or F, followed by 0 or 1, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@10C) Followed by 02 through 16, followed by 1 or 3, followed by G or H, followed by 0, 1 or 8, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@10D) Followed by 02 through 24, followed by 1 or 3, followed by 6 or 7, followed by 0, 1, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@11) Followed by 02 thru 24, followed by 0 or 9, followed by 0, 1, 6 or 7, followed by 0 thru 9 or A thru Z, followed by 0, 2 or 3, followed by four alphanumeric digits, followed by G, H or blank.

(@@12) Followed by 02 thru 24, followed by 0 or 9, followed by 0, 1, 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9, C or D, followed by 0 or 1, followed by four alphanumeric digit, followed by G, H, F or blank.

(@@12A) Followed by 02 through 24, followed by 0, 5, 7 or A, followed by A, B or C, followed by 0, 1, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@12B) Followed by 02 through 24, followed by 0, 5, 7 or A, followed by D, E or F, followed by 0 or 1, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@12C) Followed by 02 through 16, followed by 0, followed by 1 or 5, followed by 0 thru 6, 8, 9 or C, followed by A, followed by four alphanumeric digits, followed by F, G or H.

(@@12D) Followed by 02 through 24, followed by 5 or 7, followed by 6 or 7, followed by 0, 1, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@13) Followed by 04 or 06, followed by 0 thru 7, followed by 0 or 1, followed by 5, followed by 0, followed by two alphanumeric digits or blank.

(@@14) Followed by 04 or 06, followed by 0 thru 7, followed by 4 or 5, followed by 5, followed by 0, followed by two alphanumeric digits or blank.

(@@15) Followed by 01 thru 30, followed by 4 or 5, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9, B or C, followed by 0 or 1, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@15a) Followed by 01 thru 12, followed by 0 or 2, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed four alphanumeric digits, followed by F, G or H.

(@@16) Followed by 01 thru 24, followed by 0, 1 or 2, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@17) Followed by 01 thru 03, followed by 0 thru 5, followed by 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@18) Followed by 01 thru 03, followed by 2 or 3, followed by 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by two or four alphanumeric digits or blank followed by F, G, H or blank.

(@@19) Followed by 02 thru 24, followed by 1 thru 4, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B, C or D, followed by two alphanumeric digits or blank.

(@@20) Followed by 02 thru 24, followed by 1 thru 4, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 3, followed by two alphanumeric digits or blank.

(@@20A) Followed by 02 through 24, followed by 1 or 3, followed by E or F, followed by 0, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@21) Followed by 02 thru 24, followed by 5 thru 8, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B, C or D, followed by two alphanumeric digits or blank.

(@@22) Followed by 02 thru 24, followed by 5 thru 8, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 3, followed by two alphanumeric digits or blank.

(@@22A) Followed by 02 through 24, followed by 5 or 7, followed by D, E or F, followed by 0, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@23) Followed by 02 thru 10, followed by C, followed by 1, 2 or 3, followed by C, 0, 2 thru 6, 8 or 9, followed by 0 or 1, followed by 0 or 1, followed by two or three alphanumeric digits or blank, followed by F, G, H or blank.

(@@23-1) Followed by 02 thru 10, followed by C, followed by 1, 2 or 3, followed by C, 0, 2 thru 6, 8 or 9 or 5, followed by 2 or 3, followed by 0 or 1, followed by two or three alphanumeric digits or blank, followed by F, G, H or blank.

(@@24) Followed by 02 or 03, followed by 6, followed by 0, 1, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 3, followed by two or four alphanumeric digits or blank.

(@@24-1) Followed by 02 or 03, followed by 6, followed by 0, 1, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 4 or 5, followed by two or four alphanumeric digits or blank.

(@@25) Followed by 02 thru 05, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by one or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@26) Followed by 04 or 06, followed by 0, 1, 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@27) Followed by 01 thru 30, followed by 0 thru 5, followed by 0, followed by 8 or C, followed by 0, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@28) Followed by 01 thru 24, followed by 0 or 1, followed by 0, followed by C, 5 or 8, followed by 0, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@29) Followed by 02 or 03, followed by 0 thru 5, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 2, followed by two alphanumeric digits or blank.

(@@30) Followed by 02 or 24, followed by 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by two or four alphanumeric digits or blank.

(@@30a) followed by 02 thru 24, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by two or four alphanumeric digits or blank.

(@@31) Followed by 02 thru 24, followed by 5 or 6, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@32) Followed by 04 thru 48, followed by 5 or 6, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@33) Followed by 02 thru 24, followed by 3 or 4, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@34) Followed by 04 thru 48, followed by 3 or 4, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@35) Followed by 02 thru 24, followed by 3 or 4, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@36) Followed by 02 thru 24, followed by 3 or 4, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@37) Followed by 02 thru 24, followed by 5 thru 8, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@38) Followed by 04 thru 48, followed by 5 thru 8, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@39) Followed by 02 thru 12, followed by 1 or 2, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9, C or D, followed by 0, 3, or 4, followed by 0 thru 4, followed by two or three alphanumeric digits or blank, followed by F, G, H or blank.

(@@40) Followed by 04 thru 48, followed by 1 or 2, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@41) Followed by 01 thru 30, followed by 3, followed by 1, followed by 8 or A, followed by 0.

(@@42) Followed by 01 thru 30, followed by 0 thru 2, followed by 1, followed by 8 or A, followed by 0 or 1, followed by Z or blank.

(@@43) Followed by 02 thru 30, followed by 0 or 1, followed by 0 thru 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 3, followed by A5, followed by 0 thru 2, followed by 0 thru 1, followed by G, F or blank, followed by Z or blank.

(@@43A) Followed by 02 or 03, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by AA, followed by two alphanumeric digits, followed by F, G or H.

(@@44) Followed by 02 or 03, followed by 2 or 3, followed by 0 thru 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 3, followed by 00, followed by 0 thru 2, followed by 0 thru 1, followed by G, F or blank.

(@@45) Followed by 02 thru 04, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by 000, 001 or 002, followed by 0 or 1, followed by G, H, F or blank.

- (@@46) Followed by 05 thru 24, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by 000, 001 or 002, followed by 0 or 1, followed by G, H, F or blank.
- (@@47) Followed by 02 thru 24, followed by 0 or 1, followed by 0 thru 9 or E, followed by 0, 1 or 2, followed by 0, followed by 000, followed by 0 or 1, followed by G, H, F or blank.
- (@@48) Followed by 02 thru 04, followed by 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by 000, 001, 002, 9B0, 9B1 or 9B2, followed by 0 or 1, followed by G, H, F or blank.
- (@@49) Followed by 05 thru 24, followed by 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by 000, 001, 002, 9B0, 9B1 or 9B2, followed by 0 or 1, followed by G, H, F or blank.
- (@@50) Followed by 02 thru 04, followed by 4 or 5, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by 000, 001, 002, 9B0, 9B1 or 9B2, followed by 0 or 1, followed by G, H, F or blank.
- (@@51) Followed by 02 thru 04, followed by 2 thru 5, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by 000, 001 or 002, followed by 0 or 1, followed by G, H, F or blank.
- (@@52) Followed by 02 thru 24, followed by 2 thru 5, followed by 0 through 9 or E, followed by 0, 1 or 2, followed by 0, followed by 000, followed by 0 or 1, followed by G, H, F or blank.
- (@@53) Followed by 1 or 3, followed by 02 thru 30, followed by 0 thru 3, followed by 0 thru 3, followed by 0 or 1, followed by two alphanumeric digits, followed G, H, F or blank.
- (@@53a) followed by 2, followed by 02 through 30, followed by 0 through 3, followed by 0 through 3, followed by 0 through 3, followed by two alphanumeric digits, followed by G, H, F or blank.
- (@@54) Followed by 1 thru 6, followed by 02 thru 30, followed by 0 thru 3, followed by 0 thru 3, followed by 0 or 1, followed by two alphanumeric digits, followed G, H, F or blank.
- (@@55) Followed by 01 thru 24, followed by 0 or 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed two alphanumeric digits or blank.
- (@@56) Followed by 02 thru 24, followed by 3 or 4, followed by 0, followed by 0, 5, 6, 8 or C, followed by 0 or 2, followed two or four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@57) Followed by 02 thru 24, followed by 5 or 6, followed by 0, followed by 0, 5, 6, 8 or C, followed by 0 or 2, followed two or four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@57a) Followed by 02 through 24, followed by 7 or 8, followed by 0, 1, 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9, C or D, followed by 0 or 1, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@57b) Followed by 02 through 24, followed by 3 or 4, followed by 1 or 5, followed by 0, 5, 6, 8, C or D, followed by 0 or 1, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@57c) Followed by 02 through 24, followed by 5 or 6, followed by 0, 1, 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9, C or D, followed by 0 or 1, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@58) Followed by 01 thru 30, followed by 5 thru 9, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by two alphanumeric digits or blank, followed by G.
- (@@59) Followed by 02 thru 16, followed by 0 or A, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by F, G or H.

- (@@60) Followed by 02 thru 16, followed by 0 or A, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@61) Followed by 02 thru 24, followed by 5 or 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@62) Followed by 02 thru 24, followed by 5, followed by 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@63) Followed by 02 thru 24, followed by 1 or 3, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9, C or G, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@64) Followed by 01 thru 30, followed by 0, followed by 0 or 1, followed by 0 thru 6, 8, 9, A thru N or P thru R, followed by 1 or 2, followed by four alphanumeric digits, followed by G, H, F or blank, followed by Z or blank.
- (@@64a) Followed by 01 thru 30, followed by 0, followed by 0 or 1, followed by 0 thru 6, 8, 9, A thru N or P thru R, followed by 0 or 3, followed by four alphanumeric digits, followed by G, H, F or blank, followed by Z or blank.
- (@@64b) Followed by 01 thru 30, followed by 1, followed by 0 or 1, followed by 0 thru 6, 8, 9, A thru N or P thru R, followed by 0 thru 3, followed by four alphanumeric digits, followed by G, H, F or blank, followed by Z or blank.
- (@@65a) Followed by 01 thru 30, followed by B, followed by 0, followed by 0, 2, 3, 5, 8, A thru N or P thru R, followed by 0 or 3, followed by four alphanumeric digits, followed by G, H, F or blank.
- (@@65b) Followed by 01 thru 30, followed by B, followed by 0, followed by 0, 2, 3, 5, 8, A thru N or P thru R, followed by 1 or 2, followed by four alphanumeric digits, followed by G, H, F or blank.
- (@@66) Followed by 02 or 03, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@67) Followed by 01 thru 30, followed by 7, followed by 0, followed by 8 or 9, followed by 0 or 1, followed by three alphanumeric digits, followed by one alphanumeric digit or blank, followed by G, H, F or blank.
- (@@68) Followed by 02 thru 24, followed by 3 or 4, followed by 0, followed by 8 or 9, followed by 0, followed by three alphanumeric digits, followed by one alphanumeric digit or blank, followed by G, H, F or blank.
- (@@69) Followed by 02 thru 30, followed by 0, followed by 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@70) Followed by 02 thru 16, followed by 2, followed by 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@71) Followed by 02 or 03, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@72) Followed by 02 thru 24, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G, H or F.
- (@@73) Followed by 02 thru 24, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@74) Followed by 02 or 03, followed by 5 or 6, followed by 0, 1, 2 or 3, followed by 0, 5, 6, 8 or C, followed by 0 or 3, followed by B, followed by three alphanumeric digits, followed by F, G, H or blank.
- (@@75) Followed by 1, followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28 or 30, followed by 1, followed by 0 or 1, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.

(@@76) Followed by 02 thru 24, followed by 5, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric, followed by F, G or H.

(@@77) Followed by 02 thru 24, followed by 1 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, C or 9, followed by A, B, 4 or 5, followed by four alphanumeric digits, followed by G, H or F.

(@@78) Followed by 02 thru 24, followed by 1 or 3, followed by 2 or 5, followed by 0, 5, 6, 8, C or 9, followed by A or B, followed by four alphanumeric digits, followed by F, G or H.

(@@79) Followed by 02 thru 24, followed by 5, followed by 0, 1, 4 or 5, followed by 0, 5, 6, 8, C or 9, followed by A or B, followed by four alphanumeric digits, followed by G, H or F.

(@@80) Followed by 02 thru 24, followed by 5, followed by 3, 4 or 5, followed by 0, 5, 6, 8, C or 9, followed by A or B, followed by four alphanumeric digits, followed by F, G or H.

(@@81) Followed by 02 thru 24, followed by 7, followed by 0 or 1, followed by 0, 5, 6, 8, C or 9, followed by A or B, followed by four alphanumeric digits, followed by G, H or F.

(@@82) Followed by 02 thru 24, followed by 7, followed by 0, 1 or 5, followed by 0, 5, 6, 8, C or 9, followed by A or B, followed by four alphanumeric digits, followed by F, G or H.

(@@83) Followed by 02 thru 16, followed by 0 or A, followed by 0 or 1, followed by 0, 5, 6, 8, C or 9, followed by A or B, followed by four alphanumeric digits, followed by G, H or F.

(@@84) Followed by 02 thru 16, followed by 0 or A, followed by 0, 1 or 5, followed by 0, 5, 6, 8, C or 9, followed by A or B, followed by four alphanumeric digits, followed by F, G or H.

(@@85) Followed by 02 thru 24, followed by 0 or 2, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@86) Followed by 02 thru 12, followed by 1 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@87) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 0, 2, 4 or 6, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@88) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22 or 24, followed by 1, 3, 5 or 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, F, G or H.

(@@89) Followed by 02 thru 24, followed by A, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@90) Followed by 02 thru 24, followed by 51, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G, H or F.

(@@91) Followed by 02 thru 24, followed by 0, followed by 0, followed by 0, followed by 0, followed by four alphanumeric digits, followed by G, H or F.

(@@92) Followed by 02 thru 12, followed by 11, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G, H or F.

(@@93) Followed by 02 thru 12, followed by 1, followed by 0, followed by 0, followed by 0, followed by four alphanumeric digits, followed by G, H or F.

(@@94) Followed by 02 or 03, followed by 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@95) Followed by 02 thru 24, followed by 2 or 3, followed by B, followed by 0, 1 or 2, followed by 0, 1 or A, followed by four alphanumeric digits, followed by F, G or H.

(@@96) Followed by 02 or 03, followed by 0 or 1, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2, followed by four alphanumeric digits, followed by F, G or H.

(@@97) Followed by 02 thru 24, followed by 50, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by F, G or H.

(@@98) Followed by 02 thru 24, followed by 50, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@99) Followed by 02 or 03, followed by 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@100) Followed by 04 or 06, followed by 0 thru 3, followed by 0, 1, 6 or 7, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed 0, followed by four alphanumeric digits, followed by F, G or H.

- (@@101) Followed by 02 thru 16, followed by 0 or A, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B, C or D, followed by four alphanumeric digits, followed by G, F or H.
- (@@102) Followed by 02 thru 16, followed by 0 or A, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, F or H.
- (@@103) Followed by 02 thru 24, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@104) Followed by 02 thru 24, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@105) Followed by 02 thru 24, followed by 00, followed by 5 or 9, followed by 00000, followed by G or F.
- (@@106) Followed by 02 or 03, followed by 0, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@107) Followed by 02 or 03, followed by 0 thru 5, followed by 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by H, G or F.
- (@@108) Followed by 02 or 03, followed by 0 thru 3, followed by 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by H, G or F.
- (@@108a) Followed by 02 thru 16, followed by 0, 2 or 4, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by H, G or F.
- (@@108b) Followed by 02 thru 08, followed by 1, 3 or 5, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by H, G or F.
- (@@108c) Followed by 02 thru 16, followed by 0 or 2, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by H, G or F.
- (@@108d) Followed by 02 thru 16, followed by 0, followed by 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2, followed by four alphanumeric digits, followed by H, G or F.
- (@@108e) Followed by 02 thru 16, followed by 4, followed by 2, 3 or 6, followed by 0 thru 9 or A thru Z, followed by A, followed by four alphanumeric digits, followed by F, G or H.
- (@@109) Followed by 02 thru 24, followed by 5, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A or B, followed by four alphanumeric digits, followed by G, H or F.
- (@@110) Followed by 02 thru 24, followed by 5, followed by 3 or 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@111) Followed by 02 or 03, followed by 4 or 5, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@112) Followed by 02 or 03, followed by 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@113) Followed by 02 thru 24, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@114) Followed by 02 thru 24, followed by 0 or 1, followed by 2, 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 3, followed by C, followed by three alphanumeric digits, followed by G, H or F.
- (@@115) Followed by 02 thru 24, followed by 0 or 1, followed by 0 thru 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, followed by four alphanumeric digits, followed by F, G or H.
- (@@116) Followed by 02 thru 16, followed by 4 or 5, followed by 0 thru 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, followed by four alphanumeric digits, followed by F, G or H.
- (@@117) Followed by 02 thru 24, followed by 0 or 1, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

- (@@118) Followed by 04 or 06, followed by 0 thru 7, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G, H or F.
- (@@119) Followed by 06 or 09, followed by 0 thru 3, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G, H or F.
- (@@120) Followed by 02 thru 24, followed by 1 or 3, followed by 0 or 1, followed by 0 thru 9 or CA thru Z, followed by 0, 2 or 3, followed by 0 thru 4, followed by two alphanumeric digits or blank, followed by Z or blank.
- (@@121) Followed by 02 thru 24, followed by 1 thru 4, followed by 1, 2 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9, C or D, followed by 0 or 1, followed by two alphanumeric digits or blank, followed by Z or blank.
- (@@122) Followed by 02 thru 24, followed by 0 or 9, followed by 0, 1, 6 or 7, followed by 0 thru 9 or CA thru Z, followed by 0, 2 or 3, followed by two alphanumeric digits or blank.
- (@@123) Followed by 02 thru 24, followed by 0 or 9, followed by 0, 1, 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9, C or D, followed by 0 or 1, followed by two alphanumeric digits or blank.
- (@@124) Followed by 02 thru 24, followed by 1 thru 4, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B, C or D, followed by four alphanumeric digits, followed by F, G or H.
- (@@125) Followed by 02 thru 24, followed by 1 thru 4, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 through 3 or blank, followed by four alphanumeric digits, followed by F, G or H.
- (@@126) Followed by 02 thru 24, followed by 5 thru 8, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B, C or D, followed by four alphanumeric digits, followed by F, G or H.
- (@@127) Followed by 02 thru 24, followed by 5 thru 8, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 through 3 or blank, followed by four alphanumeric digits, followed by F, G or H.
- (@@127A) followed by 02 through 24, followed by 7, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@128) Followed by 02 thru 24, followed by 41, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by 0000, 000A, 9B00 or 9B0A, followed by G.
- (@@129) Followed by 01 thru 12, followed by 0 or 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G, H, or F.
- (@@130) Followed by 01 thru 24, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G, H or F.
- (@@131) Followed by 01 thru 12, followed by 1 or 2, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G, H or F.
- (@@132) Followed by 02 through 16, followed by 0, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@133) Followed by 02 through 16, followed by 0, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@134) Followed by 02 through 24, followed by 0 or 1, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@135) Followed by 02 through 24, followed by 0 or 1, followed by A, followed by 0, 1 or 2, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@136) Followed by 02 through 45, followed by 0 or 1, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or F.

- (@@136a) Followed by 02 through 45, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@137) Followed by 02 thru 20, followed by 0, 1, 2 or 3, followed by 0, 1, 2 or 3, followed by 0 or 1, followed by two alphanumeric digits, followed by G, H or F.
- (@@138) Followed by 02 thru 18, followed by 0, 1, 2 or 3, followed by 0, 1, 2 or 3, followed by 0 or 1, followed by two alphanumeric digits, followed by G, H or F.
- (@@139) Followed by 02 thru 18, followed by 0, 1, 2 or 3, followed by 0, 1, 2 or 3, followed by 0 or 1, followed by two alphanumeric digits, followed by G, H or F.
- (@@139a) Followed by 02 thru 18, followed by 0 or 2, followed by 0, 1, 2 or 3, followed by 0 thru 3, followed by two alphanumeric digits, followed by G, H or F.
- (@@139b) Followed by 02 thru 18, followed by A or B, followed by 0, 1, 2 or 3, followed by 0 thru 3, followed by two alphanumeric digits, followed by G, H or F.
- (@@140) Followed by 01 thru 24, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by H, G or F.
- (@@141) Followed by 01 thru 12, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by H, G or F.
- (@@142) Followed by 01 thru 24, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by H, G or F.
- (@@143) Followed by 01 thru 24, followed by 0, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by H, G or F.
- (@144) Followed by 02 or 03, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@145) Followed by 02 thru 24, followed by 1 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2 thru 5, followed by four alphanumeric digits, followed by F, G or H.
- (@@145a) followed by 01 thru 30, followed by B, followed by 2, followed by 0, 2, 3, 5, 8, A thru N or P thru R, followed by 0 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@145b) followed by 01 thru 30, followed by B, followed by 2, followed by 0, 2, 3, 5, 8, A thru N or P thru R, followed by 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@146) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 1 or 3, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@147) Followed by 02 thru 12, followed by 6, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@148) Followed by 02 thru 12, followed by 6, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@149) Followed by 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@150) Followed by 2, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@151) Followed by 02 or 03, followed by 0, 1, 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, four alphanumeric digits, followed by F, G or H.
- (@@152) Followed by 02 or 03, followed by 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, four alphanumeric digits, followed by F, G or H.
- (@@153) Followed by 02 thru 06, followed by 0, followed by 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, four alphanumeric digits, followed by F, G or H.
- (@@154) Followed by 04 or 06, followed by 0, 1, 2 or 3, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1, or 3, followed by four alphanumeric digits, followed by F, G or H.

(@@155) Followed by 02, 03 or 04, followed by 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 6, followed by four alphanumeric digits, followed by F, G or H.

(@@156) Followed by 02, 03 or 04, followed by 7, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@157) Followed by 01 thru 10, followed by D, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.

(@@158) Followed by 02 or 03, followed by 2, followed by 0, 1, 6 or 7, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by three alphanumeric digits, followed by 0, followed by F, G or H.

(@@159) Followed by 02 thru 24, followed by 0 or 1, followed by 0, 1, 2, 3, 6 or 7, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G, H or blank, followed by Z or blank.

(@@159A) Followed by 02 thru 24, followed by 0 or 1, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 2, 3, 5 or 6, followed by four alphanumeric digits, followed by F, G, H.

(@@160) Followed by 02 thru 24, followed by 0 or 1, followed by , M, C, T, N, R, D, G, A, U, Q or S, followed by 0, 1 or 2, followed by 0, followed by four alphanumeric digits, followed by F, G, H or blank, followed by Z or blank.

(@@160a) Followed by 02 thru 24, followed by 0 or 1, followed by , M, C, T, N, R, D, G, A, U, Q or S, followed by 0, 1 or 2, followed by 1, followed by four alphanumeric digits, followed by F, G, H or blank, followed by Z or blank.

(@@161) Followed by 02 thru 30, followed by 0, followed by 0 thru 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.

(@@161a) Followed by 02 thru 09, followed by 0, followed by 0 thru 3, followed by 2 or 3, followed by two alphanumeric digits, followed by F, G or H.

(@@162) Followed by 02 thru 31, followed by 0, followed by 0 thru 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.

(@@163) Followed by 02 thru 31, followed by 3, followed by 0 thru 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.

(@@164) Followed by 02 thru 32, followed by 0, followed by 0 thru 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.

(@@165) Followed by 02 thru 24, followed by 2, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 3, 4 or 5, followed by followed by four alphanumeric digits, followed by F, G or H.

(@@166) Followed by 02 thru 24, followed by 0, followed by 0, 1, 2, 3, 6 or 7, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.

(@@167) Followed by 02 thru 12, followed by 1, followed by 0, 1, 2, 3, 6 or 7, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.

(@@167A) Followed by 02 thru 24, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 3, followed by four alphanumeric digits, followed by F, G or H.

(@@167B) Followed by 02 thru 12, followed by 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 3, followed by four alphanumeric digits, followed by F, G or H.

(@@168) Followed by 02 thru 30, followed by 0, followed by 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.

(@@169) Followed by 03 thru 05, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0 thru 9 or A thru Z, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.

(@@170) Followed by 02 thru 99, followed by 0 or 2, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

- (@@170A) Followed by 02 thru 50, followed by 1 or 3, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@171) Followed by 02 thru 24, followed by 0 or 2, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@172) Followed by 02 thru 12, followed by 1 or 3, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@172A) Followed by 02 thru 99, followed by 0 or 2, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@172B) Followed by 02 thru 50, followed by 1 or 3, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@172C) Followed by 02 thru 24, followed by 0 or 2, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@172D) Followed by 02 thru 12, followed by 1 or 3, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@173) Followed by 02 through 24, followed by 5 or 7, followed by 0, 1, 6 or 7, followed by 0 thru 9 or CA thru Z, followed by 4 or 5, followed by four alphanumeric digits, followed by G, H or blank.
- (@@174) Followed by 02 through 16, followed by A, followed by 0, 1, 6 or 7, followed by 0 thru 9 or CA thru Z, followed by 0 or 2, followed by four alphanumeric digits, followed by G or H.
- (@@175) Followed by 02 through 16, followed by A, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@175A) Followed by 02 through 24, followed by 7 or A, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@175B) Followed by 02 through 24, followed by 5, followed by 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@175C) Followed by 02, followed by 5 or 7, followed by E or F, followed by 0, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@176) Followed by 02 through 24, followed by 7, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@177) Followed by 02 thru 24, followed by 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@178) Followed by 02 thru 24, followed by 1, followed by 1, 2 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@179) Followed by 02 thru 24, followed by 1, followed by 1, 2 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A or B, followed by four alphanumeric digits, followed by F, G or H.
- (@@180) Followed by 02 thru 24, followed by 0 or 5, followed by 1 or 2, followed by 0 thru 9 or A thru Z, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@181) Followed by 02 thru 24, followed by 0 or 5, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@181a) Followed by 02 thru 18, followed by 5, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@182) Followed by 02 thru 24, followed by B or 5, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@183) Followed by 02 thru 24, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or, followed by 0 thru 3, followed by four alphanumeric digits, followed by F, G or H.

- (@@184) Followed by 02 thru 24, followed by 7, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or, followed by 0 thru 5, followed by four alphanumeric digits, followed by F, G or H.
- (@@185) Followed by 02 thru 24, followed by 7, followed by 1, 2, A or B, followed by 0, 2, 3, 4, 5, 6, 8, 9 or, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@185A) Followed by 02 thru 24, followed by 7, followed by C or D, followed by 0, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@185B) Followed by 02 thru 12, followed by 8, followed by 1, 2, A or B, followed by 0, 2, 3, 4, 5, 6, 8, 9 or, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@185C) Followed by 02 thru 12, followed by 8, followed by C or D, followed by 0, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@186) Followed by 02 thru 12, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@187) Followed by 02 or 03, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by C, followed by four alphanumeric digits, followed by F, G or H.
- (@@188) Followed by 02 thru 99, followed by 6, followed by 0, 1, 2, 3, 4 or 5, followed by 0 thru 9 or A thru Z, followed by 5, followed by four alphanumeric digits, followed by F, G or H.
- (@@189) Followed by 02 thru 99, followed by 6, followed by 0, 1, 2, 3, 4 or 5, followed by 0 thru 9 or A thru Z, followed by 4 or 7, followed by four alphanumeric digits, followed by F, G or H.
- (@@190) Followed by 02 thru 99, followed by 8, followed by 0, 1, 2, 3, 4 or 5, followed by 0 thru 9 or A thru Z, followed by 5, followed by four alphanumeric digits, followed by F, G or H.
- (@@191) Followed by 02 thru 99, followed by 8, followed by 0, 1, 2, 3, 4 or 5, followed by 0 thru 9 or A thru Z, followed by 4 or 7, followed by four alphanumeric digits, followed by F, G or H.
- (@@192) Followed by 02 thru 30, followed by 3, followed by 0 thru 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (@@193) Followed by 0, followed by 0 thru 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (@@194) Followed by 02 thru 30, followed by 0, followed by 0 thru 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (@@195) Followed by 02 thru 32, followed by 0, followed by 0 thru 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (@@196) Followed by 02, 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40 and 42, followed by 1 or 3, followed by 0 thru 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (@@197) Followed by 02 through 04, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by 000, 001, 002, 9B0, 9B1 or 9B2, followed by 0 or 1, followed by G, H, F or blank.
- (@@198) Followed by 05 through 24, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by 000, 001, 002, 9B0, 9B1 or 9B2, followed by 0 or 1, followed by G, H, F or blank..
- (@@199) Followed by 01 thru 24, followed by 0 thru 2, followed by 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G, H or blank, followed by Z or blank.
- (@@200) Followed by 01 thru 24, followed by 0 thru 5, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@201) Followed by 01 thru 24, followed by 0 thru 5, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

- (@@202) Followed by 02, 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 0, 2 thru 5, followed by 0, followed by 0, 1, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@203) Followed by 03, 06, 09, 12, 15, 18, 21, 24, 27, 30, 33, 36, 39, 42, 45, 48, 51, 54, 57, 60, 63, 66, 69 or 72, followed by 3 thru 5, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@204) Followed by 02 thru 24, followed by B, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@205) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by B, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@206) Followed by 02 thru 24, followed by B, followed by 1, followed by 0, 1, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@206A) Followed by 02 thru 24, followed by B, followed by B, followed by 0, 1, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@206B) Followed by 02 thru 24, followed by B, followed by E, followed by 0 or 1, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@207) Followed by 02 thru 24, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@208) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 1, followed by 3 or 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@209) Followed by 02 thru 24, followed by 1, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@210) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 1, followed by 1 thru 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@211) Followed by 02 thru 24, followed by 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@212) Followed by 02 thru 24, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@213) Followed by 02 thru 16, followed by 2, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@213a) Followed by 02 through 24, followed by 7 or 8, followed by 0, 1, 3, 4 or 5, followed by 0, 5, 6, 8, C or D, followed by 0 or 1, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@214) Followed by 02 thru 24, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@214a) Followed by 02 through 24, followed by 5 or 6, followed by 0, 1, 3, 4 or 5, followed by 0, 5, 6, 8, C or D, followed by 0 or 1, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@214b) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 1, followed by 0, followed by 0 thru 9 or A thru Z, followed by 0, 1 or 2, followed by A, followed by three alphanumeric digits, followed by F, G or H.
- (@@215) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 1, followed by 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@215a) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 1, followed by A, B or C, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@216) Followed by 02 through 24, followed by 3 or 4, followed by 1 or 5, followed by 0, 5, 6, 8, C or D, followed by 0 or 1, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.

(@@217) Followed by 02 through 24, followed by 5 through 8, followed by 0, 1, 3, 4 or 5, followed by 0, 5, 6, 8, C or D, followed by 0 or 1, followed by two alphanumeric digits or blank.

(@@218) Followed by 02 through 24, followed by 1 or 3, followed by 2 or 3, followed by 0 thru 9 or A thru Z, followed by 0, 2 or 3, followed by 0 through 4, followed by 0000 or three alphanumeric digits, followed by G, H, Z or blank.

(@@219) Followed by 02 through 24, followed by 1 or 3, followed by 2 or 3, followed by 0 thru 9 or CA thru Z, followed by 0, 2 or 3, followed by 0 through 4, followed by two alphanumeric digits or blank, followed by Z or blank.

(@@220) Followed by 02 through 24, followed by 0 or 9, followed by 2 or 3, followed by 0 thru 9 or A thru Z, followed by 0, 2 or 3, followed by four alphanumeric digits, followed by G, H or blank.

(@@221) Followed by 02 through 24, followed by 5 or 7, followed by 2 or 3, followed by Socket:, followed by 4 or 5, followed by four alphanumeric digits, followed by G, H or blank.

(@@222) Followed by 02 through 24, followed by 0 or 9, followed by 2 or 3, followed by Socket:, followed by 0, 2 or 3, followed by two alphanumeric digits or blank.

(@@223) Followed by 02 through 16, followed by A, followed by 2 or 3, followed by 0 thru 9 or CA thru Z, followed by 0 or 2, followed by four alphanumeric digits, followed by G or H.

(@@224) Followed by 02 through 16, followed by 0 or A, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1 or 3, followed by four alphanumeric digits, followed by G, H or F.

(@@225) Followed by 02 through 16, followed by 0 or A, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.

(@@226) Followed by 02 through 24, followed by 5 or 7, followed by 0, 1, 6 or 7, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by G, H or F.

(@@227) Followed by 02 through 24, followed by 5, followed by 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.

(@@228) Followed by 02 through 24, followed by 7, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.

(@@229) Followed by 02 through 24, followed by 5, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by G, H or F.

(@@229A) Followed by 02 through 24, followed by 5, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by B, followed by four alphanumeric digits, followed by G, H or F.

(@@229B) Followed by 02 through 12, followed by 6, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by B, followed by four alphanumeric digits, followed by G, H or F.

(@@230) Followed by 02 through 24, followed by 5, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.

(@@230A) Followed by 02 through 12, followed by 6, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.

(@@230B) Followed by 02 through 24, followed by 5, followed by C or D, followed by 0, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.

(@@230C) Followed by 02 through 12, followed by 6, followed by C or D, followed by 0, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.

(@@230D) Followed by 02 through 24, followed by 5, followed by 1, followed by 0 thru 9 or A thru Z, followed by A or B, followed by four alphanumeric digits, followed by G, H or F.

(@@230E) Followed by 02 through 12, followed by 6, followed by 1, followed by 0 thru 9 or A thru Z, followed by A or B, followed by four alphanumeric digits, followed by G, H or F.

(@@231) Followed by 02 thru 12, followed by 6, followed by 0, 2, 3, 6 or 7, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@232) Followed by 02 or 03, followed by 2, followed by 0, 1, 6 or 7, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by three alphanumeric digits, followed by Z, followed by F, G or H.

(@@232a) Followed by 02 thru 24, followed by 2, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits or blank, followed by F, G or H.

(@@233) Followed by 02, 03, 04 or 06, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@234) Followed by 02 thru 24, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@235) Followed by 02 thru 12, followed by 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@236) Followed by 02 thru 24, followed by 0, followed by 0, followed by 0 thru 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@237) Followed by 02 thru 16, followed by 1 or 2, followed by 0, followed by 0 thru 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@237a) Followed by 02 thru 16, followed by 2, followed by 0, followed by 0 thru 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@238) Followed by 02 thru 24, followed by 5 or 7, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B, C or D, followed by four alphanumeric digits, followed by F, G or H.

(@@239) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 5 or 7, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@240) Plug: Cat. No. V7, followed by 02 thru 24, followed by 1, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@241) Socket: Cat. No. H5, followed by 02 thru 24, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.

(@@242) Plug: Cat. No. V7, followed by 02 thru 24, followed by 3, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@243) Socket: Cat. No. H5, followed by 02 thru 24, followed by 3, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.

(@@244) Followed by 02 thru 24, followed by 5 or 7, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

- (@@244a) Followed by 02 thru 16, followed by 0 or A, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@245) Followed by 02 thru 24, followed by 5 or 7, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@245a) followed by 02 thru 16, followed by 0 or A, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@246) Followed by 02 or 03, followed by 0 through 3, followed by 0 thru 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 through 3, followed by C500, followed by F, G or H.
- (@@247) Followed by 02 thru 24, followed by 5 or 7, followed by 0 or 1, followed by 0 thru 9 or CA thru Z, followed by 0, 2, 3, 4, 5, 6 or 7, followed by four alphanumeric digits, followed by Y.
- (@@247a) Followed by 02 thru 24, followed by 5 or 7, followed by 2, 3, 4 or 5, followed by 0 thru 9 or CA thru Z, followed by 0, 2, 3, 4, 5, 6 or 7, followed by four alphanumeric digits, followed by Y.
- (@@248) Followed by 02 through 24, followed by 5, followed by 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.
- (@@249) Followed by 02 through 24, followed by 7, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.
- (@@250) Followed by 02 thru 16, followed by 0 or A, followed by 0 or 1, followed by 0 thru 9 or CA thru Z, followed by 0 or 2, followed by four alphanumeric digits, followed by Y.
- (@@250a) Followed by 02 thru 16, followed by 0 or A, followed by 2, 3, 4 or 5, followed by 0 thru 9 or CA thru Z, followed by 0 or 2, followed by four alphanumeric digits, followed by Y.
- (@@251) Followed by 02 through 16, followed by 0 or A, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.
- (@@252) Followed by 02 through 24, followed by 5 or 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B, C or D, followed by four alphanumeric digits, followed by G, F or H.
- (@@253) Followed by 02 through 24, followed by 5, followed by 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, F or H.
- (@@254) Followed by 02 through 24, followed by 7, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, F or H.
- (@@255) Followed by 02 through 16, followed by 0 or A, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B, C or D, followed by four alphanumeric digits, followed by Y.
- (@@256) Followed by 02 through 16, followed by 0 or A, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.
- (@@257) Followed by 02 through 24, followed by 5 or 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B, C or D, followed by four alphanumeric digits, followed by Y.
- (@@258) Followed by 02 through 24, followed by 5, followed by 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.
- (@@259) Followed by 02 through 24, followed by 7, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.

- (@@260) Followed by 02 or 03, followed by 0 or 1, followed by 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@261) Followed by 02 through 16, followed by 0 or A, followed by 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B, C or D, followed by four alphanumeric digits, followed by G, F or H.
- (@@262) Followed by 02 through 24, followed by 5 or 7, followed by 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B, C or D, followed by four alphanumeric digits, followed by G, F or H.
- (@@263) Followed by 02 through 24, followed by 5 through 8, followed by 0, 1, 6 or 7, followed by 0 thru 9 or CA thru Z, followed by 0, 2 or 3, followed by four alphanumeric digits, followed by G, H or blank, followed by Z or blank.
- (@@264) Followed by 02 through 24, followed by 5 through 8, followed by 2 or 3, followed by Socket:, followed by 0, 2 or 3, followed by four alphanumeric digits, followed by G, H or blank, followed by Z or blank.
- (@@265) Followed by 02 through 24, followed by 5 or 7, followed by 0, 1, 6 or 7, followed by 0 thru 9 or CA thru Z, followed by 6 or 7, followed by four alphanumeric digits, followed by G, H or blank, followed by Z or blank.
- (@@265A) Followed by 02, followed by 5, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by A, followed by four alphanumeric digits, followed by F, G or H.
- (@@265B) Followed by 02, followed by 5, followed by F, followed by 0 or 1 followed by F, followed by four alphanumeric digits, followed by F, G or H.
- (@@266) Followed by 02 through 24, followed by 5 or 7, followed by 2 or 3, followed by Socket:, followed by 6 or 7, followed by four alphanumeric digits, , followed by G, H or blank, followed by Z or blank.
- (@@267) Followed by 02 through 24, followed by 5 through 8, followed by 0, 1, 6 or 7, followed by 0 thru 9 or CA thru Z, followed by 0, 2 or 3, followed by two alphanumeric digits or blank, followed by Z or blank.
- (@@268) Followed by 02 through 24, followed by 5 through 8, followed by 2 or 3, followed by Socket:, followed by 0, 2 or 3, followed by two alphanumeric digits or blank, followed by Z or blank.
- (@@269) Followed by 02 through 24, followed by 5 through 8, followed by 0, 1, 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9, C or D, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H, F or blank, followed by Z or blank.
- (@@270) Followed by 02 through 24, followed by 5 through 8, followed by 0, 1, 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9, C or D, followed by 0 or 1, followed by two alphanumeric digits or blank, followed by Z or blank.
- (@@271) Followed by 02 or 03, followed by 0 or 1, followed by 0 thru 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 through 3, followed by 00, followed by 0 through 2, followed by 0 through 1, followed by G, F or blank, followed by Z.
- (@@272) Followed by 02 or 03, followed by 0 or 1, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 3, followed by B, followed by three alphanumeric digits, followed by F, G, H or blank, followed by Z or blank.
- (@@273) Followed by 06 or 09, followed by 0 or 2, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by 0000, followed by G or H.
- (@@274) Followed by 02 or 03, followed by 6, followed by 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by 0000, followed by G or H.
- (@@275) Followed by 01 thru 16, followed by 0 or 1, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by 0000, followed by G or H.

- (@@276) Followed by 02 thru 24, followed by 0, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@277) Followed by 02 thru 12, followed by 1, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@278) Followed by 02 through 24, followed by 0, followed by 0, followed by 0, 1 or 2, followed by 0, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@279) Followed by 02 through 12, followed by 1, followed by 0, followed by 0, 1 or 2, followed by 0, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@279A) Followed by 02 through 24, followed by 0, followed by 0, followed by 0, 1 or 2, followed by 1, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@279B) Followed by 02 through 12, followed by 1, followed by 0, followed by 0, 1 or 2, followed by 1, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@280) Followed by 02 thru 12, followed by 6, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@281) Followed by 02 thru 12, followed by 6, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@282) (For future use)
- (@@283) Followed by 03, followed by 1, 3, 5 or 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@284) Followed by 02 thru 24, followed by 0 thru 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 3, 4 or 5, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@285) Followed by 02 thru 16, followed by 4 thru 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 3, 4 or 5, followed by two or four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@285A) Followed by 02 thru 24, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A or B, followed by four alphanumeric digits or blank, followed by F, G, H or blank.
- (@@286) Followed by 02 through 24, followed by 2 or 4, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9, C or D, followed by 0, 2 or 3, followed by 0 thru 4, followed by 0000 or three alphanumeric digits, followed by G, H, Z or blank.
- (@@287) Followed by 02 thru 24, followed by 2 or 4, followed by 0 or 1, followed by 0 thru 9 or CA thru Z, followed by 0, 2 or 3, followed by 0 thru 4, followed by two alphanumeric digits or blank, followed by Z or blank.
- (@@288) Followed by 02 through 24, followed by 2 or 4, followed by 2 or 3, followed by 0 thru 9 or CA thru Z, followed by 0, 2 or 3, followed by 0 through 4, followed by 0000 or three alphanumeric digits, followed by G, H, Z or blank.
- (@@289) Followed by 02 through 24, followed by 2 or 4, followed by 2 or 3, followed by 0 thru 9 or CA thru Z, followed by 0, 2 or 3, followed by 0 through 4, followed by two alphanumeric digits or blank, followed by Z or blank.
- (@@290) Followed by 01 thru 24, followed by 2, followed by 0 thru 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by H, G or blank.
- (@@291) Followed by 02 through 24, followed by 7, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digit, followed by G or H.

- (@@291a) Followed by 02 through 24, followed by 5, followed by 0, followed by 0, 1, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 2 or 6, followed by four alphanumeric digit, followed by G or H.
- (@@292) Followed by 02 through 24, followed by 5 or 7, followed by 0, 1, 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digit, followed by G, H or F.
- (@@293) Followed by 02 through 16, followed by 0 or A, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digit, followed by G or H.
- (@@294) Followed by 02 through 16, followed by 0 or A, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digit, followed by G, H or F.
- (@@295) Followed by 02 or 03, followed by 2, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@296) Followed by 02 or 03, followed by 2, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@297) Followed by 06 or 09, followed by 0, 1, 2 or 3, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@298) Followed by 1 or 2, followed by 02 thru 10, followed by 0 or 2, followed by 0, 1, 2 or 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (@@299) Followed by 02 thru 24, followed by 3, followed by 0, 1, 2, or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@300) Followed by 04 thru 48, followed by 3, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@301) Followed by 02 thru 24, followed by 5 or 7, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@302) Followed by 02 thru 24, followed by 5, followed by 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@303) Followed by 02 thru 24, followed by 7, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@304) Followed by 02, 03 or 04, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@305) Followed by 02 thru 24, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@305a) Followed by 02 thru 24, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, followed by four alphanumeric digits, followed by F, G or H.
- (@@306) Followed by 01 thru 24, followed by 3, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@307) Followed by 02 thru 24, followed by 1 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@308) Followed by 02 thru 12, followed by 2 or 4, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@309) Followed by 01 thru 16, followed by 0, followed by 0 thru 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, 2, 4 or 5 followed by four alphanumeric digits, followed by F, G or H.
- (@@310) Followed by 01 thru 16, followed by 0, followed by 0 thru 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@311) Followed by 01 thru 12, followed by 2, followed by 0 thru 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1 or 2, followed by four alphanumeric digits, followed by F, G or H.

(@@311a) Followed by 01 thru 12, followed by 2, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by B or C, followed by four alphanumeric digits, followed by F, G or H.

(@@312) Followed by 01 thru 12, followed by 2, followed by 0 thru 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@312a) Followed by 01 thru 12, followed by 2, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, followed by four alphanumeric digits, followed by F, G or H.

(@@313) Followed by 02 thru 24, followed by 3, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by F, G or H.

(@@314) Followed by 02 thru 24, followed by 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by F, G or H.

(@@315) Followed by 02 thru 20, followed by 0, followed by 0, 1, 2 or 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.

(@@316) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@317) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 1, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@317a) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22 or 24, followed by 2, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@317b) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 1, followed by 0, 1 or 2, followed by 0 or 1, followed by A or B, followed by four alphanumeric digits, followed by F, G or H.

(@@317c) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22 or 24, followed by 2, followed by 0, 1 or 2, followed by 0 or 1, followed by A or B, followed by four alphanumeric digits, followed by F, G or H.

(@@318) Followed by 02 or 03, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.

(@@319) Followed by 02 thru 24, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 3, 4 or 5, followed by four alphanumeric digits, followed by F, G or H.

(@@320) Followed by 02 or 03, followed by 0 through 3, followed by 0 or 1, followed 0, 5, 6 or 8, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

(@@321) Followed by 02 or 03, followed by 0 through 3, followed by 0 or 1, followed 0, 5, 6 or 8, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@322) Followed by 02 or 03, followed by 0 through 3, followed by 0 or 1, followed by 0, 5, 6 or 8, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@323) Followed by 02 thru 24, followed by 0 through 3, followed by 0 or 1, followed by 0, 5, 6 or 8, followed by 1, followed by four alphanumeric digits, followed by F, G or H.

(@@324) Followed by 02 or 03, followed by 0 through 5, followed by 0, 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 2, followed by four alphanumeric digits, followed by F, G or H.

(@@325) Followed by 02 thru 24, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 3, 4 or 5, followed by four alphanumeric digits, followed by F, G or H.

(@@326) Followed by 02 thru 16, followed by 0 or A, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by Y.

(@@327) Followed by 02 thru 16, followed by 0 or A, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.

(@@328) Followed by 02 thru 24, followed by 5 or 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by Y.

- (@@329) Followed by 02 thru 24, followed by 5, followed by 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.
- (@@330) Followed by 02 through 24, followed by 7, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.
- (@@331) Followed by 02 thru 24, followed by 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@332) Followed by 03 or 04, followed by 0, followed by 0, 1 or 2, followed by 0, 5, 6, 8 or C, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@333) Followed by 02 thru 24, followed by 0 or 5, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.
- (@@334) Followed by 02 thru 24, followed by 0 or 5, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by Y.
- (@@334a) Followed by 02 thru 24, followed by 5, followed by 0, followed by 0 thru 9 or A thru Z, followed by 0 thru 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@335) Followed by 02 through 24, followed by 5, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 3, followed by four alphanumeric digits, followed by G, H or F.
- (@@336) Followed by 02 through 24, followed by 7, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by G, H or F.
- (@@337) Followed by 02 through 24, followed by 5, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 3, followed by four alphanumeric digits, followed by Y.
- (@@338) Followed by 02 through 24, followed by 7, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by Y.
- (@@339) Followed by 02 through 24, followed by 5, followed by 3, 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.
- (@@340) Followed by 02 through 24, followed by 7, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.
- (@@341) Followed by 02 thru 16, followed by 0 or 2, followed by 0, 1, 2 or 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (@@342) Followed by 01 thru 24, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by three alphanumeric digits, followed by F, G or H.
- (@@343) Followed by 02 thru 24, followed by 3, followed by 0, followed by 0 thru 9 or A thru Z, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@343a) Followed by 04, 06, 08, 10 or 12, followed by 3, followed by 0, followed by 0 thru 9 or A thru Z, followed by A, followed by four alphanumeric digits, followed by F, G or H.
- (@@343b) Followed by 02 thru 24, followed by 3, followed by 0, followed by 0 thru 9 or A thru Z, followed by 4, 5, 6 or 7, followed by four alphanumeric digits, followed by F, G or H.
- (@@344) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 3, followed by 1, 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@344a) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 3, followed by A, B or C, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@344b) Followed by 04, 06, 08, 10 or 12, followed by 3, followed by D, followed by 0 thru 9 or A thru Z, followed by 1, followed by four alphanumeric digit, followed by F, G or H.
- (@@344c) Followed by 02 thru 24, followed by 3, followed by 8, followed by 0 thru 9 or A thru Z, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@345) Followed by 02 thru 24, followed by 5 or 7, followed by 0, followed by 0 thru 9 or A thru Z, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.

- (@@346) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 5 or 7, followed by 1, 2, 3 or 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@346a) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22 or 24, followed by 6 or 8, followed by 1, 2, 3 or 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@347) Followed by 02 thru 24, followed by 0, followed by 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@348) Followed by 02 thru 24, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@349) Followed by 02 or 03, followed by 2, followed by 2 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@350) Followed by 08 or 12, followed by 0 or 2, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@351) Followed by 02 thru 10, followed by C, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@352) Followed by 04, followed by C, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@353) Followed by 02 thru 10, followed by C, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@354) Followed by 04, followed by C, followed by 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@355) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38, 40, 42, 44, 46 or 48, followed by 0, followed by 0, 1, 2 or 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (@@356) Followed by 02 thru 24, followed by 0, followed by 0, 1, 2 or 3, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (@@357) Followed by 02 thru 12, followed by 6, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@358) Followed by 02 thru 12, followed by 6, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@359) Followed by 02, 03 or 04, followed by 0 or 1, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0.
- (@@360) Followed by 02, 03 or 04, followed by 0 or 1, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@361) Followed by 02 or 03, followed by 0 or 1, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@362) Followed by 02 thru 24, followed by 0, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 4 or 5, followed by four alphanumeric digits, followed by F, G or H.
- (@@363) Followed by 02 thru 12, followed by 1, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 4 or 5, followed by four alphanumeric digits, followed by F, G or H.
- (@@364) Followed by 02 thru 24, followed by 0, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@365) Followed by 02 thru 12, followed by 1, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@366) Followed by 04 or 06, followed by 0 through 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G, H or F.
- (@@367) Followed by 04 or 06, followed by 0 through 7, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G, H or F.

- (@@368) Followed by 04 or 06, followed by 6 or 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@369) Followed by 04 or 06, followed by 6 or 7, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@370) Followed by 01 thru 24, followed by 3, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G, H or F.
- (@@371) Followed by 01 thru 24, followed by 0, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@372) Followed by 01 thru 12, followed by 1, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@373) Followed by 01 thru 16, followed by 2, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@374) Followed by 01 thru 24, followed by 4, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@375) Followed by 01 thru 24, followed by 5 or 7, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@376) Followed by 01 thru 16, followed by 4 or 9, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@377) Followed by 01 thru 12, followed by 6 or 8, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@378) Followed by 01 through 24, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@379) Followed by 02 through 24, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by G, H or F.
- (@@380) Followed by 02 through 16, followed by 2 or 3, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by G, H or F.
- (@@381) Followed by 02 through 16, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2, followed by four alphanumeric digits, followed by G, H or F.
- (@@382) Followed by 02 through 16, followed by 0, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G, H or F.
- (@@383) Followed by 03 or 04, followed by 6, followed by 0, 1, 2, 3, 6 or 7, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@384) Followed by 02 thru 99, followed by 6 or 8, followed by 0, 1, 2, 3, 4 or 5, followed by 0 thru 9 or A thru Z, followed by 8, followed by four alphanumeric digits, followed by F, G or H.
- (@@385) Followed by 02 thru 24, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G or H.
- (@@386) Followed by 02 thru 16, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G or H.
- (@@387) Followed by 02 thru 12, followed by 2, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by G or H.
- (@@388) Followed by 02 thru 24, followed by 7, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@389) Followed by 02 thru 16, followed by A, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@390) Followed by 02 thru 24, followed by 3, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@391) Followed by 02 thru 24, followed by 3, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@392) Followed by 02 thru 24, followed by 3, followed by 0 thru 3, followed by 0 thru 9 or A thru Z, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.

- (@@393) Followed by 02 thru 24, followed by 3, followed by 1 or 2, followed by 0 thru 9 or A thru Z, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@394) Followed by 02 thru 24, followed by 5, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0 thru 5, followed by four alphanumeric digits, followed by F, G or H.
- (@@395) Followed by 02 thru 24, followed by 5 or 6, followed by 0, followed by 0 thru 9 or A thru Z, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@335a) Followed by 02 thru 24, followed by 3, followed by 0, followed by 0 thru 9 or A thru Z, followed by 0 thru 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@396) Followed by 02 thru 24, followed by 5, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@397) Followed by 02 thru 24, followed by 5, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 thru 5, followed by four alphanumeric digits, followed by F, G or H.
- (@@398) Followed by 02 through 16, followed by 0, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B or C, followed by four alphanumeric digits, followed by F, G or H.
- (@@399) Followed by 03 or 04, followed by 0, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by D, followed by four alphanumeric digits, followed by F, G or H.
- (@@400) followed by 02 through 16, followed by 0, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@401) Followed by 03 or 04, followed by 0, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@402) Followed by 08, 12, 16, 20, 24, 28, 32, 36, 40, 44, 48, 52, 56, 60, 64, 68, 72, 76, 80, 84, 88, 92 or 96, followed by 0 or 3, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@403) Followed by 08, 12, 16, 20, 24, 28, 32, 36, 40, 44, 48, 52, 56, 60 or 64, followed by 1 or 5, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@404) Followed by 08, 12, 16, 20, 24, 28, 32, 36, 40, 44 or 48, followed by 2 or 4, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@405) Followed by 02 through 30, followed by 0 or 3, followed by 0 through 3, followed by one or three alphanumeric digits, followed by Z.
- (@@406) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34, 36, 38 or 40, followed by 0, followed by 0, 1, 2 or 3, followed by 0 or 1, followed by four alphanumeric digits, followed by G or H.
- (@@407) Followed by 02 thru 10, followed by 6, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@408) Followed by 02 or 03, followed by 0 or 1, followed by 0 or 1, followed by 0, 5, 6, 8 or C, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by G or H.
- (@@409) Followed by 02 thru 24, followed by 1, followed by 0, followed by 0, 1, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@410) Followed by 02 thru 24, followed by 1, followed by 0, followed by 0, 1, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@410a) Followed by 02 thru 24, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A or B, followed by four alphanumeric digits, followed by F, G or H.
- (@@410b) Followed by 02 thru 24, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by C, followed by four alphanumeric digits, followed by F, G or H.
- (@@411) Followed by 02 thru 20, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@412) Followed by 02 thru 10, followed by 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

- (@@413) Followed by 02 thru 24, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@414) Followed by 02 thru 12, followed by 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@415) Followed by 02 thru 04, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@415a) Followed by 01 thru 99, followed by 7, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@416) Followed by 02 thru 24, followed by 1 or 7, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@417) Followed by 02 or 03, followed by 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@418) Followed by 02 or 03, followed by 7, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@419) Followed by 02 or 03, followed by 8, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@420) Followed by 02 or 03, followed by 8, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@421) Followed by 02 thru 12, followed by 0, followed by 0, followed by 0, 1 or 2, followed by 0, 1, 2 or 3 followed by four alphanumeric digits, followed by F, G, H or blank.
- (@@422) Followed by 02 thru 06, followed by 1, followed by 0, followed by 0, 1 or 2, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by F, G, H or blank.
- (@@423) Followed by 02 thru 24, followed by 5, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@424) Followed by 02 thru 12, followed by 6, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@424a) Followed by 02 thru 24, followed by 7, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@424b) Followed by 02 thru 12, followed by 8, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@425) Followed by 02, 03 or 04, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, may be followed by one digit.
- (@@426) Followed by 02 or 03, followed by 0 or 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@427) Followed by 02 or 03, followed by 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, may be followed by one digit.
- (@@428) Followed by 02 or 03, followed by 2 or 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@429) (For future use)
- (@@430) Followed by 01 thru 16, followed by A, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@431) Followed by 01 thru 16, followed by A, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@432) Followed by 02 through 16, followed by 0, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 4, followed by four alphanumeric digits, followed by F, G or H.
- (@@433) Followed by 03 or 04, followed by 0, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 5, followed by four alphanumeric digits, followed by F, G or H.
- (@@434) Followed by 02 thru 16, followed by 0, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@435) Followed by 02 or 03, followed by 1 or 2, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.

- (@@436) Followed by 01 thru 24, followed by 2, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@437) Followed by 01 thru 24, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@438) Followed by 01 through 24, followed by 3, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@439) Followed by 01 through 24, followed by 5, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@440) Followed by 02 through 24, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@441) Followed by 02 thru 24, followed by 1, followed by 2 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 2 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@441a) Followed by 02 thru 24, followed by 1, followed by 2 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A or B, followed by four alphanumeric digits, followed by F, G or H.
- (@@442) Followed by 01 thru 12, followed by 1, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8 or 9, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@443) followed by 01 thru 12, followed by 1, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8 or 9, followed by 1 or 2, followed by four alphanumeric digits, followed by Followed, G or H.
- (@@444) Followed by 02 through 24, followed by 5, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, 1, 2, or A followed by four alphanumeric digits, followed by F, G or H.
- (@@445) Followed by 02 thru 24, followed by 5, followed by 3 thru 6, followed by 0 thru 9 or A thru Z, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@446) Followed by 02 through 16, followed by 0, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by E, F or G, followed by four alphanumeric digits, followed by F, G or H.
- (@@447) Followed by 02 through 08, followed by 1, followed by 0, 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by E, F or G, followed by four alphanumeric digits, followed by F, G or H.
- (@@448) Followed by 02 through 16, followed by 0, followed by 0, 1 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B or C, followed by four alphanumeric digit, followed by F, G or H.
- (@@449) Followed by 02 through 08, followed by 1, followed by 0, 1 or 3, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by A, B or C, followed by four alphanumeric digit, followed by F, G or H.
- (@@449a) Followed by 02 through 06, followed by 0, followed by 0, followed by 0 thru 9 or A thru Z, followed by E or F, followed by four alphanumeric digits, followed by F, G or H.
- (@@449b) Followed by 02 thru 99, followed by 0, followed by 0 thru 9 or A thru Z, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (@@449c) Followed by 0 thru 9 or A thru Z, followed by 0, 4, 6, 8, A or B, followed by 0 thru 9 or A thru Z, followed by two alphanumeric digits, followed by F, G or H.
- (@@450) Followed by 02 thru 24, followed by 3, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@451) Followed by 02 through 24, followed by 3, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@452) Followed by 02 thru 12, followed by 4, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@453) Followed by 02 through 12, followed by 4, followed by 1 or 2, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@454) Followed by 01 thru 10, followed by C, followed by 1, 2 or 3, followed by 0 thru 9 or A thru Z, followed by 2 or 3, followed by 0 or 1, followed by three or four alphanumeric digits, followed by F, G or H.

- (@@454a) Followed by 01 thru 08, followed by D, followed by 4, followed by 0 thru 9 or A thru Z, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@455) Followed by 01 through 24, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@456) Followed by 02 through 16, followed by 0 or A, followed by 4 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1 or 3, followed by four alphanumeric digits, followed by Y.
- (@@457) Followed by 02 through 16, followed by 0 or A, followed by 0, 1 or 5, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by Y.
- (@@458a) Followed by 02 through 24, followed by 0, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed four alphanumeric digits, followed by Y.
- (@@458b) Followed by 02 through 12, followed by 1, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed four alphanumeric digits, followed by Y.
- (@@459a) Followed by 02 through 24, followed by 0, followed by 0 through 9 or E, followed by 0, 1 or 2, followed by 0, followed four alphanumeric digits, followed by Y.
- (@@459b) Followed by 02 through 12, followed by 1, followed by 0 through 9 or E, followed by 0, 1 or 2, followed by 0, followed four alphanumeric digits, followed by Y.
- (@@460a) Followed by 02 through 24, followed by 5, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@460b) Followed by 02 through 12, followed by 6, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@461a) Followed by 02 through 24, followed by 5, followed by 3 or 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@461b) Followed by 02 through 12, followed by 6, followed by 3 or 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@462a) Followed by 01 thru 12, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8 or 9, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@462b) Followed by 02 thru 12, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8 or 9, followed by 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@462c) Followed by 01 thru 12, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8 or 9, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@463a) Followed by 01 thru 24, followed by 0, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@463b) Followed by 01 thru 24, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@464) Followed by 01 thru 24, followed by 3, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits, followed by G.
- (@@465) Followed by 02 thru 24, followed by 2, followed by 0 or 1, followed by 0 or 1, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@466) Followed by 02 thru 12, followed by 3, followed by 0 or 1, followed by 0 or 1, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@467) Followed by 04 thru 48, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@468) Followed by 04 thru 24, followed by 2, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@468a) Followed by 04 thru 48, followed by 1, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@468b) Followed by 04 thru 24, followed by 2, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1 or 2, followed by four alphanumeric digits, followed by F, G or H.

- (@@468c) Followed by 04 thru 36, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@468d) Followed by 04 thru 18, followed by 2, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@468e) Followed by 04 thru 36, followed by 1, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@468f) Followed by 04 thru 18, followed by 2, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@469) Followed by 04 through 48, followed by 1 or 2, followed by 1, followed by 0 or 1, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@470) Followed by 04 through 24, followed by 1 or 2, followed by 1, followed by 0 or 1, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@470a) Followed by 04 through 24, followed by 2, followed by 1 or 2, followed by 0 or 1, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@470b) Followed by 04 through 12, followed by 2, followed by 1 or 2, followed by 0 or 1, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@470c) Followed by 04 through 48, followed by 1, followed by 3 or 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@470d) Followed by 04 through 24, followed by 1, followed by 3 or 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@470e) Followed by 04 through 24, followed by 2, followed by 3 or 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@470f) Followed by 04 through 12, followed by 2, followed by 3 or 4, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@470g) Followed by 04 through 40, followed by 1, followed by A or B, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@470h) Followed by 04 through 20, followed by 2, followed by A or B, followed by 0, 2, 3, 4, 5, 6, 8, 9 or A thru Z, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@470i) Followed by 04 through 40, followed by 1, followed by C or D, followed by 0 or 1, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@470j) Followed by 04 through 20, followed by 2, followed by C or D, followed by 0 or 1, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@471) Followed by 01 thru 12, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 1 or 2, followed by four alphanumeric digits, followed by F, G or H.
- (@@472) Followed by 08, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9, or C, followed by three alphanumeric digits, followed by G.
- (@@473) Followed by 12, 22, 28 or 40, followed by 0, followed by 0, 1, 2 or 3, followed by 0 or 1, followed by two alphanumeric digits, followed by G or H.
- (@@474) Followed by 02 through 24, followed by 5 or 6, followed by 4 or 5, followed by 0 thru 9 or C, followed by A, followed by four alphanumeric digits, followed by F, G or H.
- (@@475) Followed by 02 through 16, followed by 7 or 8, followed by 5, followed by 0 thru 9 or C, followed by A, followed by four alphanumeric digits, followed by F, G or H.
- (@@476) Followed by 01 thru 15, followed by 0, followed by 0, 1 thru 6, 8, 9 or C, followed by three alphanumeric digits, followed by F, G or H.
- (@@477) Followed by 02 thru 12, followed by 0 or 2, followed by 0 thru 3, followed by 0 or 1, followed by two alphanumeric digits, followed by G or H.

(@@477a) Followed by 02 thru 12, followed by 0 or 2, followed by 0 thru 3, followed by 2 or 3, followed by 1, followed by one alphanumeric digit, followed by G or H.

(@@478) Followed by 01 thru 12, followed by 00, followed by 0 thru 6, 8, 9 or C, followed by A or B, followed by four alphanumeric digits, followed by F, G or H.

(@@479) Followed by 01 thru 12, followed by 10, followed by 0 thru 6, 8, 9 or C, followed by A or B, followed by four alphanumeric digits, followed by F, G or H.

(@@479a) followed by 01 thru 99, followed by 20, followed by 0 thru 9 or A thru Z, followed by C or E, followed by four alphanumeric digits, followed by F, G or H.

(@@479b) followed by 01 thru 99, followed by 20, followed by 0 thru 9 or A thru Z, followed by D or F, followed by four alphanumeric digits, followed by F, G or H.

(@@480) Followed by 01 thru 24, followed by 0 thru 6, 8, 9 or C, followed by 0 or 2, followed by two alphanumeric digits, followed by F, G or H.

(@@481) Followed by 02 thru 12, followed by 0 thru 6, 8, 9 or C, followed by 1 or 3, followed by two alphanumeric digits, followed by F, G or H.

(@@482) Followed by 02 or 04, followed by 0 thru 6, 8, 9 or C, followed by 0, followed by two alphanumeric digits, followed by F, G or H.

(@@483) Followed by 04, followed by 0, followed by 0 or 1, followed by 0 thru 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@484) Followed by 01 through 24, followed by 3 or 4, followed by A, followed by 0 thru 6, 8, 9 or C, followed by five alphanumeric digits, followed by F, G or H.

(@@485) Followed by 01 through 24, followed by 5 or 6, followed by A, followed by 0 thru 6, 8, 9 or C, followed by five alphanumeric digits, followed by F, G or H.

(@@486) Followed by 01 through 24, followed by 0, followed by 0, followed by 0 thru 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@487) Followed by 01 through 12, followed by 1, followed by 0, followed by 0 thru 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@488) Followed by 01 through 24, followed by 2, followed by B, followed by 0, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@489) Followed by 01 through 12, followed by 3, followed by B, followed by 0, followed by 0, followed by four alphanumeric digits, followed by F, G or H.

(@@490) Followed by 03 thru 72, followed by 0 thru 6, 8, 9 or C, followed by 1, followed by three alphanumeric digits, followed by F, G or H.

(@@491) followed by 52, followed by 0 thru 6, 8, 9 or C, followed by 0, followed by three alphanumeric digits, followed by F, G or H.

(@@492) Followed by 01 thru 24, followed by 7 or 8, followed by 0, followed by 0 thru 9 or C, followed by 2, followed by four alphanumeric digits, followed by G, H, F.

(@@493) Followed by 01 thru 24, followed by 1, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits or blank, followed by F, G or H.

(@@494) Followed by 01 thru 12, followed by 2, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0 or 1, followed by four alphanumeric digits or blank, followed by F, G or H.

(@@495) Followed by 01 thru 24, followed by 1, followed by 0, followed by 0, 1 or 2, followed by 1, followed by four alphanumeric digits or blank, followed by F, G or H.

(@@496) Followed by 01 thru 12, followed by 2, followed by 0, followed by 0, 1 or 2, followed by 1, followed by four alphanumeric digits or blank, followed by F, G or H.

(@@497) Followed by 02 thru 99, followed by 0, followed by 1, 2 or 3, followed by 0 thru 9 or A thru Z, followed by 0, followed by four alphanumeric digits or blank, followed by F, G or H.

(@@498) Followed by 08, followed by 0, followed by 0 thru 6, 8, 9 or A thru Z, followed by three alphanumeric digits, followed by F, G or H.

(@@499) Followed by 02, followed by 0, followed by 0 thru 6, 8, 9 or A thru Z, followed by two alphanumeric digits, followed by 1 or 2, followed by F, G or H.

- (@@500) Followed by 02 thru 16, followed by B, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9, or A thru Z, followed by 0 or 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@501) Followed by 02 thru 16, followed by C, followed by 1, followed by 0, 2, 3, 4, 5, 6, 8, 9, or A thru Z, followed by 0, 1, 2 or 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@502) Followed by 02 thru 16, followed by C, followed by E, followed by 0, 2, 3, 4, 5, 6, 8, 9, or A thru Z, followed by 0, 1, 2, 3, A, B, C or D, followed by four alphanumeric digits, followed by F, G or H.
- (@@503) Followed by 02 through 99, followed by 0 thru 9 or A through Z, followed by one alphanumeric digit, followed by 7 or 8, followed by one alphanumeric digit, followed by F, G or H.
- (@@504) Followed by 02 through 24, followed by 0, followed by A, C, D, G, M, L, followed by 0, 1 or 2, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@505) Followed by 02 through 24, followed by 0, followed by A, C, D, G, M, L, followed by 0, 1 or 2, followed by 1, followed by four alphanumeric digits, followed by F, G or H.
- (@@506) Followed by 02, 03 or 04, followed by 1, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@507) Followed by 01 thru 12, followed by 1, followed by 0 or 1, followed by 0 thru 9 or A thru Z, followed by 0, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@508) Followed by 02 thru 12, followed by 0 or 2, followed by 0, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digit, followed by F, G or H.
- (@@509) Followed by 01 thru 99, followed by 1 or 2, followed by 0, followed by 0 thru 9 or A thru Z, followed by 0, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@510) Followed by 01 thru 99, followed by 1, followed by 0, followed by 0 thru 9 or A thru Z, followed by 1, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@511) Followed by 01 thru 99, followed by 2, followed by 0, followed by 0 thru 9 or A thru Z, followed by 1, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@512) Followed by 01 thru 99, followed by 3, followed by 0, followed by 0 thru 9 or A thru Z, followed by 0, followed by four alphanumeric digits or blank, followed by F, G or H.
- (@@513) Followed by 04, 06, 08, 10, 12, 14, 16, 18, 20, 22, 24, 26, 28, 30, 32, 34 or 36, followed by 1, followed by 0, followed by 0 thru 9 or A thru Z, followed by 3, followed by four alphanumeric digits, followed by F, G or H.
- (@@514) Followed by 01 thru 02, followed by 0, followed by 0 thru 9 or A thru Z, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (@@515) Followed by 02, 04, 06, 08, 10, 12, 14 or 16, followed by 1, followed by 0 thru 9 or A thru Z, followed by 0 or 1, followed by two alphanumeric digits, followed by F, G or H.
- (@@516) Followed by 02 thru 14, followed by 1, followed by 0 thru 9 or A thru Z, followed by three alphanumeric digits, followed by F, G or H.
- (@@517) Followed by 01 thru 24, followed by 0 or 2, followed by 0 or 1, followed by 0, 2, 3, 4, 5, 6, 8, 9 or C, followed by 0, followed by four alphanumeric digits, followed by F, G or H.
- (@@518) Followed by 02 thru 07, followed by 0, followed by 0, followed by 0 thru 9 or A thru Z, followed by two alphanumeric digits, followed by F, G or H.

#6 Model TJ 5.0 and OQ 5.0; TJ 5.08 and OQ 5.08 are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#7 Model VD and VE Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#8 Model TJ and OQ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#9 Model TS and VK Series, with letter 1 thru 4 for fifth digit of catalog number, are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#10 Model TS and VK Series, with letter 5 thru 8 for fifth digit of catalog number, are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#11 Model VH and VL with letter 5 or 6 for fifth digit of catalog number; VM and VL with letter 3 or 4 for fifth digit of catalog number; VM and VZ with letter 3 or 4 for fifth digit of catalog number; VM and VL with letter 5 thru 8 for fifth digit of catalog number; TJ and VL with letter 1 or 2 for fifth digit of catalog number are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#12 Model TH and OP with letter 2 or 3 for fifth digit of catalog number; Model TT with letter 4 or 5 for fifth digit of catalog number and Model OP with letter 2 or 3 for fifth digit of catalog number; Model TH and OP with letter 4 or 5 for fifth digit of catalog number; Model TT with letter 2 or 3 for fifth digit of catalog number and Model OP with letter 4 or 5 for fifth digit of catalog number; Model TH and OP with letter 0 or 1 for fifth digit of catalog number; Model TT and OP with letter 0 or 1 for fifth digit of catalog number are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#13 Model HI and OQ Series; Model HW and OQ Series; Model HN and OQ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#14 Model EM with letter 0 for eighth digit of catalog number and OQ with 0 or 1 for sixth digit of catalog number; Model EM with letter 2 for eighth digit of catalog number and OQ with 5 for sixth digit of catalog number are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#15 Model EM with letter 0 for eighth digit of catalog number and OQ with 3 or 4 for sixth digit of catalog number; Model EM with letter 2 for eighth digit of catalog number and OQ with 5 for sixth digit of catalog number are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#16 These models have been evaluated for it's suitability as protective conductor terminal blocks and complies with the applicable grounding requirements for terminals for use in a protective cirCuit.

#17 Model VB and VC Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#18 The terminal blocks Cat. No. YK77 Series consist of two halves with plug consisting of the pressure wire terminals and the socket consisting of the soldering terminals. These devices have not been evaluated to make or break the flow of Current. These devices are not evaluated for use with any other mating connectors.

#19 Model TJ and OQ Series with letter 1 or 3 for fifth digit of catalog number are intended mating together to become a terminal block assembly. Among those models, Model TJ Series with letter A for eighth digit of catalog number is intended to mate with Model OQ Series with letter 2 for sixth digit of catalog number. And Model TJ Series with letter B for eighth digit of catalog number is intended to mate with Model OQ Series with letter 5 for sixth digit of catalog number. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#20 Model TJ and OQ Series with letter 5 for fifth digit of catalog number are intended mating together to become a terminal block assembly. Among those models, Model TJ Series with letter A for eighth digit of catalog number is intended to mate with Model OQ Series with letter 3 or 4 for sixth digit of catalog number. And Model TJ Series with letter B for eighth digit of catalog number is intended to mate with Model OQ Series with letter 5 for sixth digit of catalog number. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#21 Model TJ and OQ Series with letter 0, 7 or A for fifth digit of catalog number are intended mating together to become a terminal block assembly. Among those models, Model TJ Series with letter A for eighth digit of catalog number is intended to mate with Model OQ Series with letter 0 or 1 for sixth digit of catalog number. And Model TJ Series with letter B for eighth digit of catalog number is intended to mate with Model OQ Series with letter 5 for sixth digit of catalog number. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#22 Model EP Series with letter 0 for fifth digit of catalog number and Model EO Series with letter 5 for fifth digit of catalog number are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#23 Model EP Series with letter 1 for fifth digit of catalog number and Model EO Series with letter 1 for fifth digit of catalog number are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#24 Model EH Series with letter 2 for fifth digit of catalog number and Model OP Series with letter 2 for fifth digit of catalog number are intended mating together to become a terminal block assembly. Model EH Series with letter 3 for fifth digit of catalog number and Model OP Series with letter 3 for fifth digit of catalog number are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#25 Model HP Series and Model VZ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#26 The terminal blocks consist of two halves with plug consisting of the pressure wire terminals and socket consisting of the soldering terminals. These devices have not been evaluated to make or break the flow of Current. These devices as tabulated below are not evaluated for use with any other mating connectors.

Plug	Socket
TS with letter A for fifth digit of catalog number and letter A or B for eighth digit of catalog number	OQ with letter A for fifth digit of catalog number and letter 0 or 1 for sixth digit of catalog number
TS with letter A for fifth digit of catalog number and letter C or D for eighth digit of catalog number	OQ with letter A for fifth digit of catalog number and letter 5 for sixth digit of catalog number
TS with letter 0 for fifth digit of catalog number and letter A or B for eighth digit of catalog number	OQ with letter 0 for fifth digit of catalog number and letter 0 or 1 for sixth digit of catalog number
TS with letter 0 for fifth digit of catalog number and letter C or D for eighth digit of catalog number	OQ with letter 0 for fifth digit of catalog number and letter 5 for sixth digit of catalog number
TS with letter 5 for fifth digit of catalog number and letter A or B for eighth digit of catalog number	OQ with letter 5 for fifth digit of catalog number and letter 3 or 4 for sixth digit of catalog number

TS with letter 5 for fifth digit of catalog number and letter C or D for eighth digit of catalog number	OQ with letter 5 for fifth digit of catalog number and letter 5 for sixth digit of catalog number
TS with letter 7 for fifth digit of catalog number and letter A or B for eighth digit of catalog number	OQ with letter 7 for fifth digit of catalog number and letter 0 or 1 for sixth digit of catalog number
TS with letter 7 for fifth digit of catalog number and letter C or D for eighth digit of catalog number	OQ with letter 7 for fifth digit of catalog number and letter 5 for sixth digit of catalog number

Model TS with letter A for fifth digit of catalog number and letter A or B for eighth digit of catalog number and Model OQ with letter A for fifth digit of catalog number and letter 0 or 1 for sixth digit of catalog number are intended mating together to become a terminal block assembly. Model TS with letter A for fifth digit of catalog number and letter C or D for eighth digit of catalog number and Model OQ with letter A for fifth digit of catalog number and letter 5 for sixth digit of catalog number are intended mating together to become a terminal block assembly. Model TS with letter 0 for fifth digit of catalog number and letter A or B for eighth digit of catalog number and Model OQ with letter 0 for fifth digit of catalog number and letter 0 or 1 for sixth digit of catalog number are intended mating together to become a terminal block assembly. Model TS with letter 0 for fifth digit of catalog number and letter C or D for eighth digit of catalog number and Model OQ with letter 0 for fifth digit of catalog number and letter 5 for sixth digit of catalog number are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#27 Model TX with letter 0 for fifth digit of catalog number and Model EX with letter 0 for fifth digit of catalog number are intended mating together to become a terminal block assembly. Model TX with letter 1 for fifth digit of catalog number and EX with letter 1 for fifth digit of catalog number are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#28 Model EY Series and Model OQ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#29 Model ET Series and Model VC Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#30 Model VG Series and Model OP Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#31 Model TJ Series and Model VO Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#32 Model EV Series and Model EW Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#33 Model TJ Series and Model EU Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#34 Model TY Series and Model OP Series are intended mating together to become a terminal block assembly. Model TY Series and Model FW Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#35 Model E2 Series and Model EL Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#36 Model V7 and KI Series and Model V8 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#37 Model HI Series and Model NB Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#38 Model HI Series and Model NC Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#39 Model YK661 Series consist of two halves, one consisting of the pressure wire terminals and another consisting of the soldering terminals. These devices have not been evaluated to make or break the flow of Current. These devices are not evaluated for use with any other mating connectors.

#40 Model HW Series with letter B for fifth digit of catalog number and Model VL Series with letter B for fifth digit of catalog number are intended mating together to become a terminal block assembly. Model HW Series with letter B for fifth digit of catalog number and Model OQ Series with letter B for fifth digit of catalog number are intended mating together to become a terminal block assembly. Model HW Series with letter 1 for fifth digit of catalog number and letter 0 for eighth digit of catalog number and Model VL Series with letter 1 for fifth digit of catalog number and letter 3 for sixth digit of catalog number are intended mating together to become a terminal block assembly. Model HW Series with letter 1 for fifth digit of catalog number and letter 2 for eighth digit of catalog number and Model VL Series with letter 1 for fifth digit of catalog number and letter 4 for sixth digit of catalog number are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#41 Model VM Series and Model VL Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#42 Model KD Series and Model KE Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#43 Model VM Series and Model OQ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#44 Model EZ Series and Model OQ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#45 Model VR Series and Model VS Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#46 Model H4 Series and Model VF Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#47 The terminal blocks consist of two halves with plug consisting of the soldering terminals and the socket consisting of the push-in type (wire seCured by spring type action) terminals. These devices have not been evaluated to make or break the flow of Current. These devices as tabulated below are not evaluated for use with any other mating connectors.

Plug Series

Socket Series

V7 with letter 1 for fifth digit of catalog number	H5 with letter 1 for fifth digit of catalog number
--	--

#48 The terminal blocks consist of two halves with plug consisting of the soldering terminals and the socket consisting of the push-in type (wire seCured by spring type action) terminals. These devices have not been evaluated to make or break the flow of Current. These devices as tabulated below are not evaluated for use with any other mating connectors.

Plug Series	Socket Series
V7 with letter 3 for fifth digit of catalog number	H5 with letter 3 for fifth digit of catalog number

#49 The terminal blocks consist of two halves with plug consisting of the soldering terminals and the socket consisting of the push-in type (wire seCured by spring type action) terminals. These devices have not been evaluated to make or break the flow of Current. These devices as tabulated below are not evaluated for use with any other mating connectors.

Plug Series	Socket Series
V7 with letter 0, 5, 7 or A for fifth digit of catalog number	H5 with letter 0, 5, 7 or A for fifth digit of catalog number

#50 Model KR Series and Model OP Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#51 Model KK Series and Model KL Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#52 Model TJ Series and Model VF Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#53 Model HW Series and Model OQ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#54 Model HW Series and Model V5 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#55 Model VW Series and Model VX Series are intended mating together to become a terminal block assembly. Model N4 Series and Model VX Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#56 Model KD Series and Model KE Series; Model KD Series and Model OQ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#56a Model KD Series and Model OQ Series are intended mating together, see below table for details, to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly. The applicable current rating of these devices do not exceed the lesser rated current rating of Plug and/or Socket/Header.

Plug Series	Socket Series
KD with letter 5 for fifth digit and letter 0 for eighth digit of catalog number	OQ with letter 5 for fifth digit and letter 3 or 4 for sixth digit of catalog number

KD with letter 5 for fifth digit and letter 1 for eighth digit of catalog number	OQ with letter 5 for fifth digit and letter 5 for sixth digit of catalog number
KD with letter 7 for fifth digit and letter 0 for eighth digit of catalog number	OQ with letter 7 for fifth digit and letter 0 or 1 for sixth digit of catalog number
KD with letter 7 for fifth digit and letter 1 for eighth digit of catalog number	OQ with letter 7 for fifth digit and letter 5 for sixth digit of catalog number

#57 Model TX Series and Model EX Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#58 Model KX Series and Model KU Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#59 Model KJ Series and Model KK Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#60 Model HP Series and Model VZ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#61 Model V8 Series and Model V7 Series are intended mating together to become a terminal block assembly. Series KI and V8 are intended mating together to become a terminal block assembly. BThese devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#62 Model V9 Series and Model VZ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#63 Model TJ Series and Model V5 Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#64 Model ET Series and Model KT Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#65 Model KT Series and Model KS Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#66 Model HN Series and Model EL Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#67 Model NF Series and Model OQ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#68 Model ET Series and Model VC Series are intended mating together to become a terminal block assembly. Model WR018 Series and Model VC Series are intended mating together to become a terminal block assembly. Model WR01800 Series and Model VC and/or KE Series are intended mating together to become a terminal block assembly. Model WR01801 Series and Model VC and/or KE Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#69 Model K8 Series and Model VE Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#70 Model NT Series and Model OQ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#71 Models NV, NL Series and Models NW, NR Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#72 Model NU Series and Model OP Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#73 Model NY Series and Model OL Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#74 Model KD Series and Model OQ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#75 Model WB0003 Series and Model OP Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly.

#76 Model TS Series and Model OQ Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly. The applicable current rating of these devices do not exceed the lesser rated current rating of Plug and/or Socket.



#77 Model HO Series and Model PD Series are intended mating together to become a terminal block assembly. These devices have not been evaluated for use with any other mating combinations and have not been evaluated for interrupting the flow of Current by connecting or disconnecting the mating terminal block assembly. The applicable current rating of these devices do not exceed the lesser rated current rating of Plug and/or Socket.

(#) - 600V when mounted on a suitably insulated mounting surface.

(#1) - The insulating bodies are molded of materials having a maximum temperature rating of 120°C when using PBT material.

(#2) - The insulating bodies are molded of materials having a maximum temperature rating of 115°C when using Nylon material.

(#3) - These terminal blocks were tested with 3.2 mm thick PWB, with 1.6 mm wide copper traces on both sides. The suitability of printed circuit board heating on thinner PC boards, more narrow traces or single-side tracing should be determined in end use.

Marking: Company name or trademark  ,  , or "FCI", "E202113" and catalog designation (catalog designation may appear on shipping carton.)

Last Updated on 2022-09-15

The appearance of a company's name or product in this database does not in itself assure that products so identified have been manufactured under UL Solutions' Follow - Up Service. Only those products bearing the UL Mark should be considered to be Certified and covered under UL Solutions' Follow - Up Service. Always look for the Mark on the product.

UL Solutions permits the reproduction of the material contained in Product iQ subject to the following conditions: 1. The Guide Information, Assemblies, Constructions, Designs, Systems, and/or Certifications (files) must be presented in their entirety and in a non-misleading manner, without any manipulation of the data (or drawings). 2. The statement "Reprinted from Product iQ with permission from UL Solutions" must appear adjacent to the extracted material. In addition, the reprinted material must include a copyright notice in the following format: "©2022 UL LLC."

